

## Radio interference suppression filter, three phase, low leakage current **HLD 310-500/130**



### Advantages

For enhanced requirements
Low leakage current
Single-stage filter concept
Efficient filter effect against line-bound interference emissions
Increase in the interference immunity of the connected consumer

### Applications

Radio interference suppression filter for line-side interference suppression of single devices, frequency converters or as group interference suppression.


### Standards

Safety isolating transformer  
to: VDE 0570 Part 2-6, DIN EN 61558-2-6, EN 61558-2-6, IEC 61558-2-6,  
UL 5085-1/-2, CSA 22.2 No.66

### Approvals



UL 1283 5th edition, CSA 22.2 No 8



# Radio interference suppression filter, three phase, low leakage current

## HLD 310-500/130

### Electrical data

Type	HLD 310-500/130
Operating data	
Rated voltage	3 x 520 Vac
Voltage range	0 - 3 x 520 Vac
Rated current	3 x 130 A
Leakage current (50 Hz)*	<0.40 mA
Leakage current (50 Hz)**	<3.50 mA
Power loss	90.0 W
Overtopping Capacity	150 %, shortly
Input	
Rated frequency	50 - 60 Hz
Standards	
Classification	EMI filter
Approvals	
Approvals	cURus, UL 1283 5th edition, CSA 22.2 No.8
Environment	
Climatic category	25/085/21 (in accordance with EN 60068-1)
Ambient temperature max.	50 °C
Safety and protection	
SCCR***	100 kA
Type	Metal enclosure
Protection index	IP 20
Safety class (prepared)	I
Test voltage	2150 Vdc Phase/Phase, 2700 Vdc Phase/PE
Notes	
*	Leakage current measured against the maximum permissible input voltage fluctuation in accordance with IEC 38 ±10 %
**	Leakage current by loss of two phases
***	with corresponding preliminary fuse
Order numbers	
Order Number	HLD 310-500/130

### Mechanical data

Type	HLD 310-500/130
Terminal and mounting	
Connections phase	Screw clamp, 50 mm²
Connections PE	Bolt, M10
Fixing method	Mounting lugs
Fixing screws	M6
Measures and weights	
Weight	5.60 kg

