Radio interference suppression filter, three phase, low leakage current

HLD 310-500/16



Advantages

For enhanced requirements

Low leakage current

Single-stage filter concept

Efficient filter effect against line-bound interference emissions

Increase in the interference immunity of the connected consumer

Applications

Radio interference suppression filter for line-side interference suppression of single devices, frequency converters or as group interference suppression.

Standards

Radio interference suppression filter complying with DIN EN 60939-2, UL 1283, CSA C22.2 No.8 $\,$

Approvals



UL 1283 5th edition, CSA 22.2 No 8





Radio interference suppression filter, three phase, low leakage current

HLD 310-500/16

Type	HLD 310-500/16	Type
Operating data		Terminal and mountin
Rated voltage	3 x 520 Vac	Connections phase
Voltage range	0 - 3 x 520 Vac	Connections PE
Rated current	3 x 16 A	Fixing method
Leakage current (50 Hz)*	<0.40 mA	Fixing screws
Leakage current (50 Hz)**	<3.50 mA	Measures and weight
Power loss	12.0 W	- Weight
Overrating Capacity	150 %, shortly	ar
Input		Ü 220 0
Rated frequency	50 - 60 Hz	Fixing method Fixing screws Measures and weight Weight
Standards		
Classification	EMI filter	۰
Approvals		250.0
Approvals	cURus, UL 1283 5th edition, CSA 22.2 No.8	
Environment		
Climatic category	25/085/21	
	[in accordance with EN 60068-1]	
Ambient temperature max.	50 °C	
Safety and protection		
SCCR***	100 kA	
Туре	Metal enclosure	
Protection index	IP 20	
Safety class (prepared)	I	
Test voltage	2150 Vdc Phase/Phase, 2700 Vdc Phase/PE	
Notes		
*	Leakage current measured against the maximum permissible input voltage fluctuation in	
	accordance with IEC 38 ±10 %	
**	Leakage current by loss of two phases	
***	with corresponding preliminary fuse	
Order numbers		
Order Number	HLD 310-500/16	



