

# Digital Clamp Meter



## Description



This model is 4,000 count stable, safe and reliable digital clamp multimeter. It is designed with large-scale integrated circuits and A/D converter as the core as well as the overload protection and novel structure, which make them a superb tool for electricians.

## Features

- Display Count : 3,999
- Auto Range
- Jaw Capacity : 28mm
- Duty Cycle : 0.1% to 99.9%
- Diode Test
- Auto Power Off
- Continuity Buzzer
- Low Battery Indication
- Data Hold
- Relative Mode
- Setup
- Input Impedance for DCV : Around 10MΩ

## Specifications

	Range	Best Accuracy
AC Current (A)	40A/400A	±(2.5%+5)
DC Current (A)	40A/400A	±(2%+3)
AC Voltage (V)	4V/40V/400V/600V	±(1%+5)
DC Voltage (V)	400mV/4V/40V/400V/600V	±(0.8%+1)
Resistance (Ω)	400Ω/4kΩ/40kΩ/400kΩ/4MΩ/40MΩ	±(1%+2)
Capacitance (F)	4nF/40nF/400nF/4μF/40μF/100μF	-
Frequency (Hz)	10Hz to 10MHz	±(0.1%+3)
Temperature (°C)	-40°C to 1,000°C	-

## General Characteristic

Power	9V Battery (6F22)
LCD Size	35.6mm × 18mm
Product Colour	Orange and Grey
Product Net Weight	260g
Product Size	208mm × 76mm × 30mm
Standard Accessories	Battery, Test Lead, Carrying Bag
Safety Rating	CAT II 600V
	CAT III 300V

## Part Number Table

Description	Part Number
DC/AC Clamp Meter 3,999 Count	72-7224

**Important Notice :** This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

