

Power Socket



Description

Tenma's 72-13530 power socket can be used to monitor the operating status (voltage, current, time, and power consumption) of electrical appliances. Alarm will go off and display "OL" when errors are found. This power socket is ideal for maintaining equipment power consumption and a good tool for managing energy savings in homes, offices, schools, and other places.

SPECIFICATIONS

Basic Functions	Range	Best Accuracy
Voltage	100.0V~150.0V	±1%
Current	0A~16.00A	±1%
Frequency	60Hz	√
Power	0~1800W	±1%
Power Factor	0~1.00	±2%
Energy consumption	0~9999KWh	±1%

Special Functions		
Unit Price of Electricity	0.00~99.99 (\$/kWh)	√
Accumulative Time	0 minute~9999Days	√
Accumulative Charge	0~9999\$	√
Power Consumption	<0.4W	√
Overload indication	>15A	√

GENERAL CHARACTERISTICS

Power	3.0 V Button Battery	
Product Color	White	
Product Net Weight	140g	
Product Size	130mm×65mm×59mm	
Standard Accessories	Batteries	

Part Number Table

Description	Part Number
Power Socket	72-13530

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com
www.farnell.com
www.newark.com
www.cpc.co.uk
www.mcmelectronics.com

