

Handheld Digital Multimeter with Bluetooth **multicomp** PRO

RoHS
Compliant



Features

- 41/2 bit resolution (20000 counts)
- Data Logger + Multimeter + Thermometer
- True RMS test supported
- BLE 4.0 wireless transmission, more stable, less power consumption
- Build-in offline record function
- Chart and Diagram mode helps to analyze the data tendency
- Flashlight function lightens the darkness
- Support NCV non-contact voltage sense
- Widely supported on Android, iOS

Specification

Note: When measuring AC voltage/current or capacitance, accuracy guarantee range is 5% to 100% of the range.

Characteristics	Instruction
Display	19999
Frequency Response (Hz)	40 Hz to 1000 Hz
Sample rate for digital data	3 times/second
Bluetooth	√
Auto ranging	√
True RMS	√
Diodes Test	√
Sleep Mode	√
Continuity Test	√
NCV function	√
Flashlight	√
Low battery indication	√(The "E+" is displayed when the battery is under the proper operation range.)
Data Hold	√
Relative Measurement	√
LCD Backlight	√
Input Protection	√
Input Impedance	≥ 10 MΩ
Battery	9V Battery (6F22)
LCD Size	58.5 mm × 41 mm
Weight (without package)	0.32 kg
Dimension	190 mm × 90 mm × 56 mm
Working temperature	0°C to 40°C
Storage temperature	-10°C to +60°C
Relative Humidity	≤ 80%
Altitude	Operating: 3,000 meters Non-operating: 15,000 meters

Handheld Digital Multimeter with Bluetooth **multicomp** PRO

Function		Measurement Range	Resolution	Function		
DC Voltage (V)	mV ⁽¹⁾	20mV	0.001mV	±(0.05%+10dig)		
		200mV	0.01mV			
	V	2V	0.1mV	±(0.1%+2dig)		
		20V	1 mV			
		200V	10mV			
		1000V	0.1V			
				±(0.15%+5dig)		
AC Voltage (V)	mV ⁽¹⁾	20mV	0.001mV	VRMS Freq range: 40Hz-1000Hz	±(0.5%+10dig)	
		200mV	0.01mV			
	V	2V	0.1mV			
		20V	1mV			
		200V	10mV			
		750V	0.1V			
				±(0.8%+10dig)		
DC Current (A)	μA	200μA	0.01μA	±(0.5%+10dig)		
	mA	2mA	0.1μA			
		20mA	1μA			
		200mA	10μA			
A	20A ⁽²⁾	1mA	±(2.0%+10dig)			
AC Current (A)	μA	200μA	0.01μA	VRMS Freq range: 40Hz-1000Hz	±(0.8%+10dig)	
	mA	2mA	0.1μA			
		20mA	1μA			
		200mA	10μA			
A	20A [2]	1mA	±(2.5%+10dig)			
Resistance (Ω)			200Ω	0.01Ω	±(0.5%+10dig)	
			2kΩ	0.1Ω	±(0.3%+3dig)	
			20kΩ	1Ω	±(0.3%+1dig)	
			200kΩ	10Ω		
			2MΩ	100Ω		
			20MΩ	1kΩ	±(0.5%+1dig)	
			200MΩ	10kΩ	±(5%+10dig)	
Capacitance (F)			2nF	0.1pF	±(3.0%+10dig)	
			20nF	1pF		
			200nF	10pF		
			2μF	100pF		
			20μF	1nF		
			200μF	10nF		
			2mF	100nF		
			20mF [3]	1μF		

Handheld Digital Multimeter with Bluetooth **multicomp** PRO

Function	Measurement Range	Resolution	Function
Frequency ^[4] (Hz)	200Hz	0.01Hz	±(0.1%+4dig)
	2kHz	0.1Hz	
	20kHz	1Hz	
	200kHz	10Hz	
	2MHz	0.1kHz	
	20MHz	1kHz	
Duty Cycle ^[5] (%)	0.1% - 99.9% (Typical: V _{rms} =1 V, f=1 kHz)	0.1%	±(1.2%+3dig)
	0.1% - 99.9%(≥1 kHz)		±(2.5%+3dig)
Temperature (°C/°F)	-50°C to 400°C	0.1°C	±(1.0%+3°C)
	-58°F to 752°F	0.1°F	±(1.2%+6°F)

[1] The rotary switch position \tilde{mV} is only for specific models.

[2] When measuring current, for 10 A to 15 A, the measuring duration should not be over 2 minutes within 10 minutes, and in this 10 minutes, no other current should flow through except within the measuring duration; for 15 A to 20 A, the measuring duration should not be over 10 seconds within 15 minutes, and in this 15 minutes, no other current should flow through except within the measuring duration.

[3] When measuring capacitance, for the 20.00mF range, the measuring duration should be over 30 seconds.

[4] When measuring frequency, the typical waveform is Square or Sine. The signal meets the following conditions.

Frequency	Amplitude (rms)
1 Hz – 4 MHz	≥ 100 mV
4 Hz – 8 MHz	≥ 200 mV
8 Hz – 10 MHz	≥ 300 mV

[5] When measuring duty cycle, the typical waveform is Square.


Accessories



Multimeter Leads



K-type thermocouple



Quick guide



9V battery (6F22)



Bolt driver



Alligator Clips

Part Number Table

Standard Warranty : 12 Months

Description	Part Number
Handheld Digital Multimeter with Bluetooth, 4-1/2 Digits	MP730624

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro
 Farnell.com/multicomp-pro
 Element14.com/multicomp-pro

multicomp PRO