

PIC18F/LF2XJ10 Plug-In Module for PICDEM™ HPC Explorer Demo Board

Overview

The PIC18F/LF2XJ10 Plug-in Module (PIM) is an accessory to the PICDEM HPC Explorer Demo board that allows users to easily experiment with the PIC18F24J10/25J10 and PIC18LF24J10/25J10 on the demo board. The PIM takes the place of the on-board PIC18F8722 device, and changes the output of the voltage regulator on the board to the proper voltage level for these parts. This enables users to quickly evaluate the new PIC18FJ Flash devices, without having to buy a completely new demo board.

Getting Started with the PIM

1. Verify that the PICDEM HPC Explorer Demo board is not powered.
2. Set switch S3 to the "ICE" position.
3. Line up the PIM so its 3-pin female header aligns with the 3-pin riser on the HPC Explorer Demo, then plug the PIM into the demo board.
4. Apply power the demo board. Be sure that V_{DD} is correct for the device being used (3.3V for a PIC18F24J10/25J10 device, or 2.7V for a PIC18LF24J10/25J10 device).

Changes to PICDEM HPC Explorer Demo Board Configuration

The difference of available I/O pins between the PICDEM HPC Explorer Demo board's PIC18F8722 device and the PIM's PIC18F2XJ10 device causes some changes in the operation of the PICDEM HPC Explorer Demo board:

1. The I/O lines connected to J3, J5, J7 and J11 will no longer be as shown on the board silkscreen. The new connections (to the microcontroller on the PIM) are shown in Figure 1 of the schematic on the back of this page.
2. The LEDs (D1 through D8) are now connected to PORTB.
3. The function of the push button switch on RB0 now overlaps with LED D1, which is also driven from PORTB<0>.
4. Only the ports shown in Figure 1 (PORTA, PORTB, PORTC and PORTD) are available. All other ports associated with the on-board PIC18F8722 are unavailable.

When using the PIC18F/LF2XJ10 PIM, replace the appropriate parts of the original schematic with the schematic parts shown in Figure 1.

For More Information

The complete schematic and user's guide for the PICDEM HPC Explorer Demo board, as well as the data sheet for the PIC18F45J10 family of microcontrollers, are available on the Microchip web site: www.microchip.com.

Americas

Atlanta - 678-957-9614
Boston - 774-760-0087
Chicago - 630-285-0071
Dallas - 972-818-7423
Detroit - 248-538-2250
Kokomo - 765-864-8360
Los Angeles - 949-462-9523
Phoenix - 480-792-7200
Santa Clara - 408-961-6444
Toronto - 905-673-0699

Asia/Pacific

Australia - Sydney - 61-2-9868-6733
China - Beijing - 86-10-8528-2100
China - Chengdu - 86-28-8665-5511
China - Fuzhou - 86-591-8750-3506
China - Hong Kong - 852-2401-1200
China - Qingdao - 86-532-8502-7355
China - Shanghai - 86-21-5407-5533
China - Shenyang - 86-24-2334-2829
China - Shenzhen - 86-755-8203-2660
China - Shunde - 86-757-2839-5507
China - Wuhan - 86-27-5980-5300
China - Xian - 86-29-8833-7250
India - Bangalore - 91-80-4182-8400
India - New Delhi - 91-11-4160-8631
India - Pune - 91-20-2566-1512
Japan - Yokohama - 81-45-471-6166
Korea - Gumi - 82-54-473-4301
Korea - Seoul - 82-2-554-7200
Malaysia - Penang - 60-4-646-8870
Philippines - Manila - 63-2-634-9065
Singapore - 65-6334-8870
Taiwan - Hsin Chu - 886-3-572-9526
Taiwan - Kaohsiung - 886-7-536-4818
Taiwan - Taipei - 886-2-2500-6610
Thailand - Bangkok - 66-2-694-1351

Europe

Austria - Weis - 43-7242-2244-39
Denmark - Copenhagen - 45-4450-2828
France - Paris - 33-1-69-53-63-20
Germany - Munich - 49-89-627-144-0
Italy - Milan - 39-0331-742611
Netherlands - Drunen - 31-416-690399
Spain - Madrid - 34-91-708-08-90
UK - Wokingham - 44-118-921-5869

12/08/06



MICROCHIP
www.microchip.com

2355 West Chandler Boulevard • Chandler, Arizona 85224-6199 • (480) 792-7200 • Fax (480) 792-7277

Information subject to change. The Microchip name and logo and the Microchip logo are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries. PICDEM is a trademark of Microchip Technology Incorporated in the U.S.A. and other countries. All other trademarks mentioned herein are property of their respective companies.
© 2007 Microchip Technology Inc. All rights reserved. Printed in the U.S.A. 01/07 DS51610A

Figure 1: PIC18F/LF2XJ10 PIM Schematic

