


Scope Digital Multimeter



Specifications:

Basic Functions	Range	Best Accuracy
DC Voltage (V)	400mV/4V/40V/400V/600V	±(0.8%+8)
AC Voltage (V)	4V/40V/400V/600V	±(1%+15)
DC Current (A)	400µA/4,000µA/40mA/400mA/4A/10A	±(1%+8)
AC Current (A)	400µA/4,000µA/40mA/400mA/4A/10A	±(1.5%+8)
Resistance (Ω)	400Ω/4kΩ/40kΩ/400kΩ/4MΩ/40MΩ	±(1%+5)
Capacitance (F)	40nF/400nF/4µF/40µF/100µF	±(3%+8)
Frequency (Hz)	10Hz - 10MHz	±(0.1%+3)

Special Functions

Display Count		4,000
Auto Range		√
Duty Cycle	0.1 to 99.9%	√
Diode		√
Auto Power Off		√
Continuity Buzzer		√
Display	160 × 160 Monochrome	√
Trigger Types	Free Run/Normal/Single Shot	√
Memory	10 screens and setups	√
Contrast and Bright Setup		√
Low Battery Indication		√
USB Interface		√
LCD Backlight		√
Input Impedance for DCV	Around 10MΩ	√

General Characteristics

Power	1.5V Cells (R6) × 4
LCD Size	60mm × 60mm
Product Color	Red and Grey
Product Net Weight	470g
Product Size	200mm × 100mm × 48mm
Standard Accessories	Cells, Test Lead, Alligator Clip, USB Interface Cable, PC Software CD, BNC Probe

Part Number Table

Description	Part Number
Scope Digital Multimeter	72-2620

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

