

multicomp PRO

RPi3 CASE, Pi-BOX PRO 3 Assembly Instructions MP004559 and MP004560


IMPORTANT SAFETY INFORMATION

When using electronic components basic safety precautions should always be followed.



WARNING: This is an electrostatic sensitive device, take precautions to ground yourself during the assembly procedure.

KIT CONTENTS




- (a) x8 M3x10 Taptite Screws
- (b) x14 M3x5 Screws
- (c) x4 12mm Stand-offs
- (d) x3 8mm Stand-offs
- (e) x1 Aluminium End Plate


- (f) x1 HDMI Extender PCB
- (g) x1 Aluminium Carrier Plate
- (h) x1 Aluminium Extrusion
- (i) x1 Acrylic End Plate

ASSEMBLY


1. Take carrier plate (g) & attach stand-offs (c) & (d) with screws (b).




2. Plug extender board (f) into the HDMI & USB connectors on the Raspberry Pi board.




3. Place Raspberry Pi & extender on carrier plate assembly & secure with screws (b) as shown.



4. Turn board assembly over so carrier plate is on top & slide into top slot of extrusion (h) as shown.



5. Attach aluminium front (e) & acrylic (i) rear plates to extrusion (h) with screws (a).



INFORMATION ON WASTE DISPOSAL FOR CONSUMERS OF ELECTRICAL & ELECTRONIC EQUIPMENT.

When this product has reached the end of its life it must be treated as Waste Electrical & Electronics Equipment (WEEE). Any WEEE marked products must not be mixed with general household waste, but kept separate for the treatment, recovery and recycling of the materials used. Contact your local authority for details of recycling schemes in your area.

Made in the UK. LS12 2QQ
 PO Box 13362 Dublin 2
 Man Rev 1.1