

Digital Clamp Meter



Specifications

Basic Functions	Range	Basic Accuracy
DC Voltage	400mV / 4V / 40V / 400V / 600V	± (0.8% +1)
AC Voltage	400mV / 4V / 40V / 400V / 600V	± (1.2% +5)
DC Current	40A / 1000A	± (1.5% +8)
AC Current	40A / 1,000A	± (2% +8)
Resistance	400Ω / 4kΩ / 40kΩ / 400kΩ / 4MΩ / 40MΩ	± (1% +2)
Frequency	4kHz / 40kHz / 400kHz / 4MHz / 40MHz	± (0.1% +3)

Features

Auto Ranging	–	√
Diode	–	√
Continuity Buzzer	–	√
True RMS	AC Voltage	√
Surge Current	AC Current	√
Peak Max / Peak Min Mode	–	√
Data Hold	–	√
Sleep Mode	–	√
Display Backlight	–	√
Full Icon Display	–	√
Low Battery Display	–	√
Input Impedance for AC Voltage Measurement	Around 10MΩ	√
Max. Display	4,000	√
Analogue Bar Graph	–	√

Digital Clamp Meter



General Characteristic	
Power	9V Alkaline Battery (1604A or 6LF22)
LCD Size	47mm × 30mm
Product Color	Orange and Grey
Product Net Weight	533g
Product Size	286mm × 105mm × 45mm
Standard Accessories	Test Lead, Alkaline Battery, English Manual, Tool Box
Standard Individual Packing	Gift Box
Standard Carton Dimensions	480mm × 372mm × 315mm (0.056 CBM Per Standard Carton)
Standard Carton Gross Weight	11 kgs.

Part Number Table

Description	Part Number
Multimeter, Digital, Clamp	72-9485

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

