

# Charger

## Ni-Cad / Ni-MH



### Features:

- Charges 1 to 2 9V Ni-Cad / Ni-MH batteries in 3 to 4 hours
- 2 individual charging channels
- Automatically switches to trickle charge after full charge
- $-\Delta V$  charging
- Discharge function
- Automatically switches to trickle charge after full charge
- LED charge status indicators
- UK plug

### Electrical Data:

Input	Input Voltage / Frequency	230V / 50HZ
	Input Power	4.7W
Output	Rated Output Voltage	9.8V
	Rate Fast Charging Current	70mA
	Rated Output Power	1.4VA
Resistance	Insulation Resistance	100M $\Omega$ (measured with 500 V DC)
Protection	Thermal Protection	Thermal fuse: 125°C / 2A
	Withstand Voltage (Hi-Pot)	3,750V AC 50Hz for 1minute or 4,000V AC 2seconds

### Mechanical Data:

Supply Connection Type	UK
Primary Turns and Wire Gauge	4,950 / 0.07mm
Secondary Turns and Wire Gauge	400T / 0.27mm
Core Size	35 × 13mm
Unit Weight	223g

### Part Number Table

Description	Part Number
Charger, 9V Plug-In Ni-Cad / Ni-MH	MW6288UK

**Important Notice :** This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.