

Battery Charger

Universal Ni-Cad / Ni-MH Desktop



Features:

- Charges 2 to 8 pieces AA / AAA and 1 to 2 pieces 9V Ni-Cad / Ni-MH batteries simultaneously
- 4 individual charging channels for AA / AAA and 2 channels for 9V
- LED charge status indicators
- UK plug

Electrical Data:

Input	Input Voltage / Frequency	240V / 50Hz
	Input Power	6.4W
Output	Rated Output Voltage	2.8V × 4/9V × 2
	Rated Output Load Current	2.8V/200mA, 9V/15mA
	Rated Output Power	2.24VA
Resistance	Insulation Resistance	100MΩ (measured with 500V DC)
Protection	Thermal Protection	Thermal fuse: 125°C / 2A
	Withstand Voltage (Hi-Pot)	3,750V AC 50Hz for 1minute or 4,000V AC 2 seconds

Mechanical Data:

Supply Connection Type	UK
Primary Turns and Wire Gauge	3,360T / 0.9mm
Secondary Turns and Wire Gauge	73T × 2 / 0.41mm, 295T / 0.11mm
Core Size	41mm × 16mm
Unit Weight	438g

Part Number Table

Description	Part Number
Charger, Universal Ni-Cad / Ni-MH, UK Plug	MW7988UK

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.