

DCA Bench Meter



Features:

- Easy operation
- Professional quality
- Compact size

Application:

Education, Maintenance, Production line, School, Laboratory, Industrial and Quality control.

Specifications:

Display	LCD, 18 mm (0.7") digit height.
Measurement	DC current
Range/ Resolution	2mA × 0.001mA
	20mA × 0.01mA
	200mA × 0.1mA
	5A × 0.01A
Accuracy	2mA / 20mA / 200mA range : ± (1.0% + 1d) @ reading
	5A range : ± (1.5% + 2d) @ reading
Voltage Drop of the full scale	2mA / 20mA / 200mA range : 200mV DC. 5A range : 50mV DC.
Over load Protection	2mA / 20mA / 200mA range : 500mA Fuse. 5A range : 10A Fuse.
Polarity	Automatic Switching '-' indicates negative polarity.
Zero Adjustment	Automatic.
Over - input	Display shows '1' or '-1'
Safety	Meet IEC1010 CATII 600V.
Sampling Time	Approx. 0.4 second.
Operating Temperature	0°C to 50°C (32°F to 122°F)
Operating Humidity	Less than 80% RH.
Power Supply	DC 9V battery.
Power Consumption	Approx. 1.3mA.
Dimension	147 x 117 x 52 mm, (5.8 x 2.6 x 4.0 inch).
Weight	313 g/0.34 LB (including battery).
Input terminal	Standard banana terminals (Red, Black, White each).
Accessory Included	Operation Manual & 1 PC.

Part Number Table

Description	Part Number
DCA Bench Meter	72-7277

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

