

Multimeter

Digital, Clamp, 3-3/4 Digit



Description:

Compact Clamp Meter w/Frequency

Perfect for general purpose applications, this compact clamp meter measures AC/DC voltage, AC/DC current, resistance, frequency and duty cycle

Features:

- 3999 count autoranging display
- 10M Ω input impedance
- 1" clamp diameter
- Relative mode
- Diode test
- Continuity buzzer
- Data hold
- Full icon display
- Sleep mode
- Low battery indicator
- Includes zipper case, test leads, owners manual
- Requires one 9V battery (292-035), included

Specification Table:

Specifications	Range	Accuracy
DC voltage	400mV, 4V, 40V, 400V, 600V	$\pm(0.8\% +1)$
AC voltage	4V, 40V, 400V, 600V	$\pm(1\% +5)$
DC current	40A, 400A	$\pm(2\% +3)$
AC current	40A, 400A	$\pm(2.5\% +5)$
Resistance	400 Ω , 4k Ω , 40k Ω , 400k Ω , 4M Ω , 40M Ω	$\pm(1\% +2)$
Frequency	10Hz to 100MHz	$\pm(0.1\% +3)$
Duty Cycle	0.1 to 99.9%	

Part Number Table

Description	Part Number
Multimeter, Digital, Clamp, 3-3/4 Digit	72-7224

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

