Product data sheet Characteristics

TM3DQ8R

module TM3 - 8 outputs relays



Main

Range of product	Modicon TM3
Product or component type	Discrete output module
Range compatibility	Modicon M221 Modicon M241 Modicon M251
Discrete output type	Relay normally open
Discrete output number	8
Discrete output logic	Positive or negative
Discrete output voltage	24 V DC for relay output
Discrete output current	200 mA for relay output

Complementary

Discrete I/O number	8
Current consumption	30 mA at 5 V DC via bus connector at state on 40 mA at 24 V DC via bus connector at state on 0 mA at 24 V DC via bus connector at state off 5 mA at 5 V DC via bus connector at state off
Response time	5 ms for turn-off 10 ms for turn-on
Mechanical durability	20000000 cycles
Minimum load	10 mA at 5 V DC for relay output
Local signalling	1 LED per channel green for output status
Electrical connection	Removable screw terminal block pitch 5.08 mm with 11 terminal(s) of 2.5 mm ² connection capacity for outputs
Cable length	<= 30 m unshielded cable cable for relay output
Insulation	1500 V AC between output groups 750 V AC between outputs 2300 V AC between output and internal logic
Marking	CE
Mounting support	Plate or panel with fixing kit Top hat type TH35-7.5 rail conforming to IEC 60715 Top hat type TH35-15 rail conforming to IEC 60715
Height	70 mm
Depth	84.6 mm
Width	27.3 mm
Product weight	0.11 kg

Environment


Standards	EN/IEC 61131-2 EN/IEC 61010-2-201
Product certifications	C-Tick CULus
Resistance to electrostatic discharge	On contact - EN/IEC 61000-4-2 In air - EN/IEC 61000-4-2
Resistance to electromagnetic fields	1 V/m (2 GHz3 GHz) - EN/IEC 61000-4-3 3 V/m (1.4 GHz2 GHz) - EN/IEC 61000-4-3 10 V/m (80 MHz1 GHz) - EN/IEC 61000-4-3
Resistance to magnetic fields	30 A/m (5060 Hz) - EN/IEC 61000-4-8
Resistance to fast transients	2 kV for relay output - EN/IEC 61000-4-4
Surge withstand	1 kV for I/O (DC) in common mode - EN/IEC 61000-4-5

Resistance to conducted disturbances, induced by radio frequency fields	3 Vrms (spot frequency (2, 3, 4, 6.2, 8.2, 12.6, 16.5, 18.8, 22, 25 MHz)) - Marine specification (LR, ABS, DNV, GL) 10 Vrms (0.1580 MHz) - EN/IEC 61000-4-6
Electromagnetic emission	Radiated emissions - EN/IEC 55011 class A 10 m, 230 MHz1 GHz : 47 dB μ V/m QP Radiated emissions - EN/IEC 55011 class A 10 m, 30230 MHz : 40 dB μ V/m QP
Ambient air temperature for operation	-1055 °C for horizontal installation -1035 °C for vertical installation
Ambient air temperature for storage	-2570 °C
Relative humidity	1095 % without condensation in storage 1095 % without condensation in operation
IP degree of protection	IP20 with protective cover in place
Pollution degree	2
Operating altitude	02000 m
Storage altitude	03000 m
Vibration resistance	3 gn (vibration frequency: 8.4150 Hz) on panel 3.5 mm (vibration frequency: 58.4 Hz) on panel 3 gn (vibration frequency: 8.4150 Hz) on DIN rail 3.5 mm (vibration frequency: 58.4 Hz) on DIN rail
Shock resistance	15 gn (test wave duration:11 ms)

Product data sheet Dimensions Drawings

TM3DQ8R


Dimensions




(*) 8.5 mm/0.33 in. when the clamp is pulled out.

TM3DQ8R


Spacing Requirements




Mounting on a Rail



Incorrect Mounting




Mounting on a Panel Surface



(1) Install a mounting strip

Mounting Hole Layout




Product data sheet Connections and Schema

TM3DQ8R


Digital Relay Output Module (8-channel)

Wiring Diagram (Positive Logic)



- (*) Type T Fuse
- (1) The COM0 and COM1 terminals are not connected internally.
- (2) To improve the life time of the contacts, and to protect from potential inductive load damage, it is recommended to connect a free wheeling diode in parallel to each inductive DC load or an RC snubber in parallel of each inductive AC load.
- (A) Source wiring (positive logic)

Wiring Diagram (Negative Logic)



- (*) Type T fuse
- (1) The COM0 and COM1 terminals are not connected internally.
- (2) To improve the life time of the contacts, and to protect from potential inductive load damage, it is recommended to connect a free wheeling diode in parallel to each inductive DC load or an RC snubber in parallel of each inductive AC load.
- (B) Sink wiring (negative logic)