

TBL70

4W- 70V, 5 Taps at -3dB Levels



GENERAL DESCRIPTION

The **TBL70** is a 4W-70V transformer with 5 taps at -3dB levels and 7" color-coded, pre-cut leads.

INTENDED USE - Indoor Environment

Primary Use	Signal tones, voice and music
Installation	Desired tap / common primary leads connected to the output of a constant voltage amplifier. Secondary / common attached to a nominal 8 Ohm loudspeaker.

AUDIO SPECIFICATIONS

Primary Volts	70.7V
Power Rating	10W
Primary Taps (-3 dB Steps)	5
Secondary Load	8-Ohms, Nominal
Frequency Response	100 Hz- 15 kHz
Insertion Loss	1.0 dB



MECHANICAL SPECIFICATIONS

Primary Connection	7" Color-Coded, Pre-Cut
Secondary Connection	6" Color-Coded, Pre-Cut
Shipping Weight	10 Oz

RECOMMENDED QUAM COMPONENTS

Loudspeakers	Any 8-Ohm device (8C10DVPAX requires two transformers)
---------------------	---

