

Voltage Tester



Specifications:

Technical Functions / Features:

Voltage LED Steps (AC/D)	12V: between 0 to 12V LED will illuminate 24V: between 19V \pm 2V LED will illuminate 50V: between 48V \pm 6V LED will illuminate 120V: between 110V \pm 20V LED will illuminate 230V: between 200V \pm 20V LED will illuminate 400V: between 340V \pm 30V LED will illuminate 690V: between 520V \pm 30V LED will illuminate
Continuity Test	Range 0 to 100k Ω . The continuity LED will illuminate and buzzer will sound.
Phase Rotation Test	50Hz to 60Hz
Range Selection	Automatic
Polarity Detection	Positive & Negative
Low Battery Display	Short circuit two leads, LED and beeper do not on that means the battery is low
Torch	√
Single Lead (L2) Voltage Detection	It is intended only as a quick check. 100V to 690V; 50Hz to 400Hz
Short Circuit Detection	√

General Characteristics:

Power	1.5V Battery (AAA) \times 2
Product Colour	Orange+Grey
Product Net Weight	210g
Product Size	275 \times 51 \times 30mm



Voltage Tester



General Characteristics:

Standard Accessories	Batteries, English Manual
Standard Individual Packing	Blister
Standard Quantity Per Carton	30pcs
Standard Carton Measurement	440 × 295 × 455mm (0.079CBM Per Standard Carton)
Standard Carton Gross Weight	17kg

Part Number Table

Description	Part Number
Voltage Tester	72-9395

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

