

# Digital Multimeter



## Description

This automotive digital multimeter is a 1,999 counts, 3½ digits manual ranging meter. Spotting a unique design with an extra large LCD display. Connect test Leads display, full overload protection and unique design. For this reason, it emerges as an electric meter with more outstanding performance for safer operation than other meters. In addition to the Dwell, Tach and Data Hold feature, the Meter can be used to test the AC voltage, DC voltage, DC current, resistance, temperature, frequency, diode and continuity.



## Features

- Display Count : 2,000
- Manual Range
- Diode Test
- Continuity Buzzer
- Low Battery Indication
- Data Hold
- Input Protection
- Input Impedance for DCV : Around 10MΩ

## Specifications

	Range	Best Accuracy
DC Voltage (V)	200mV/2V/20V/200V/1000V	±(0.5%+2)
AC Voltage (V)	200V/750V	± (0.8%+5)
DC Current (A)	200mA/10A	± (0.8%+5)
Resistance (Ω)	200Ω/2kΩ/20kΩ/200kΩ/2MΩ/20MΩ	± (0.8%+5)
Frequency (Hz)	2kHz	±(2%+5)
Temperature (°C)	-40°C to +1,000°C	±(2%+8)
Dwell	4CYL/6CYL/8CYL	±(3%+5)
Tach	4CYL/6CYL/8CYL	±(3%+5)

## General Characteristic

Power	9V Battery (6F22)
LCD Size	60mm × 54mm
Product Colour	Orange and Grey
Product Net Weight	351g (Including Holster)
Product Size	179mm × 88mm × 39mm
Standard Accessories	Battery, Test Lead, Holster, Point Contact Temperature Probe
Safety Rating	CAT II 1,000V, CAT III 600V

## Part Number Table

Description	Part Number
Multimeter, Digital, Hand Held, 3½ Digits	72-9275

**Important Notice :** This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

