

Pocket-Size Digital Multimeter



Description

The model is a portable notebook - type 3-3/4 digit auto range digital multimeter. It is fully functional, having stable performance, high accuracy, low power consumption, safe and reliable. It can be used to measure AC and DC voltage, frequency, duty cycle, resistance, capacitance, diode forward voltage drop and continuity test.



Features

- Max. Display : 3,999
- Auto Range
- Duty Cycle : 0.1% to 99.9%
- Diode Test
- Continuity Buzzer
- Relative Mode
- Data Hold
- Full Icon Display
- Sleep Mode
- Low Battery Display
- Input Impedance for DC Voltage Measurement : Around 10MΩ

Specifications

	Range	Best Accuracy
DC Voltage	400mV/4V/40V/300V	$\pm(0.8\%+1)$
AC Voltage	4V/40V/300V	$\pm(1.2\%+3)$
Resistance	400Ω/4kΩ/40kΩ/400kΩ/4MΩ/40MΩ	$\pm(1\%+2)$
Capacitance	4nF/40nF/400nF/4μF/40μF/200μF	$\pm(4\%+3)$
Frequency	10Hz/100kHz	$\pm(0.5\%+3)$

General Characteristic

Power	3V Button Cell (CR2032)
LCD Size	43mm × 22mm
Product Colour	Orange and Grey
Product Net Weight	62g
Product Size	58mm × 108mm × 12mm
Standard Accessories	Test Lead, 3V Button Cell, English Manual, Vinyl Holder

Part Number Table

Description	Part Number
Pocket-Size Digital Multimeter	72-7935

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.