

User Guide

USB Ethernet Adapter Model: USB3GIG

About This Guide

Online Resources

Resource	Website
Linksys	www.linksys.com
Linksys International	www.linksys.com/international
Glossary	www.linksys.com/glossary
Network Security	www.linksys.com/security

Copyright and Trademarks

Linksys, Belkin and the Linksys Logo are registered trademarks or trademarks of Belkin International, Inc. and/or its affiliates in the U.S. and certain other countries. Copyright ©2014 Belkin International, Inc. All rights reserved. Other brands and product names are trademarks or registered trademarks of their respective holders.

Table of Contents

CHAPTER 1 QUICK START GUIDE
LEDs 1
Ports
Installing the Adapter
CHAPTER 2 DRIVER INSTALLATION 2
Driver Installation for Windows XP
Driver Installation for Windows Vista
Driver Installation for Windows 8 and Windows 8.1 2
Driver Installation for Mac OS X
Appendix A: Troubleshooting
Appendix B: Specifications

CHAPTER 1 Product Overview

Thank you for choosing the Linksys USB Ethernet Adapter. This adapter lets you easily connect any device with a USB port – such as your computer, game console, or DVR – to a wired network. Small and light, yet rugged enough for travel, the adapter keeps you connected almost everywhere you go.

LEDs



Link/Activity (Blue) The Link/Activity LED is solid blue when there is an active link over the Ethernet interface. The LED flashes blue when data is being transferred over the Ethernet interface.

Ports



Ð	
Ш	
11	

USB This is a USB 3.0 Type A connector that you connect to an available USB port on your computer or other device. Connecting the adapter to a USB 3.0 port will yield best performance.



Ethernet This port connects the adapter to your network's router or switch.

Installing the Adapter

- 1. Remove the caps from the adapter to expose the USB and Ethernet ports.
- 2. Insert the adapter's USB connector into an available USB port on your computer or device.

NOTE:

For maximum performance, connect the adapter directly to a USB 3.0 port on your computer. If you are connecting to a USB hub, make sure it operates at USB 3.0 speed.

- 3. Insert one end of an Ethernet network cable into the adapter's RJ-45 port.
- 4. Insert the other end of the Ethernet network cable into the Ethernet port on your network's router or switch.

Chapter 2: Driver Installation

After physically connecting the adapter to your computer's USB port or hub, follow these instructions to install the hardware device driver. The installation procedures for the hardware device driver vary depending on your computer's operating system, so make sure to follow the instructions for your operating system. The instructions also may vary slightly depending on your current operating system's configuration. If at any time during the installation you encounter problems, refer to **Appendix A: Troubleshooting, page 5.**

NOTE:

Throughout this user guide, it is assumed that "D" is the letter of your CD-ROM drive.

Driver Installation for Windows XP/Vista/ Win 7/Win 8

NOTE:

Do not click Cancel at any time during the installation process. Doing so will prevent your driver from being properly installed on your computer.

- 1. If you have not yet done so, start your computer.
- 2. Insert the Drivers & Documentation CD into your CD-ROM drive
- 3. Open up the CD's folder and double-click Setup.exe.



 Linksys USB3GIGV1

 Welcome to the InstallShield Wizard for Linksys USB3GIGV1

 The InstallShield Wizard will install Linksys USB3GIGV1 on your computer. To continue, click Next.

 InstallShield

 Match IStield

InstallShield Wizard

5. Select Install



4. Select Next to advance to the next screen

6. When the driver is finished installing, click **Finish**



That's it. You're done with installation of the USB Ethernet Adapter.

For more information about networking under Microsoft Windows, refer to your Microsoft Windows documentation.

Driver Installation for Mac OS X

NOTE:

Do not click **Cancel** at any time during the installation process. Doing so will prevent your driver from being properly installed on your computer.

- 1. If you have not yet done so, start your computer.
- 2. Insert the Drivers & Documentation CD into your CD-ROM drive

3. Open up the CD's folder followed by the **MAC** folder



5. Follow the steps in the Installer application, when the installation is complete you will be asked to restart your Mac. Click the **Restart** button to finish setup.



When your Mac restarts you're done with installation of the USB Ethernet Adapter.

For more information about networking under OS X, refer to your Mac OS X documentation.

Appendix A: Troubleshooting

Your computer does not recognize the adapter.

Make sure that the adapter is properly inserted into the USB slot.

The adapter does not work properly.

Remove the adapter, and reinsert it into the computer's USB slot.



WEB: If your questions are not addressed here, refer to the Linksys website, **www.linksys.com**

Appendix B: Specifications

Model USB3GIG USB Ethernet Adapter

Standards USB 1.0, USB 1.1, USB 2.0, USB 3.0 IEEE 802.3, IEEE 802.3u

Ports One USB Type-A Male Connector, One RJ-45 Gigabit Port

Cabling Type Cat 5 Ethernet Cable

LEDs Link/Activity

Environmental

Dimensions*

7.96" x 1.00" x 0.69" (202.3 x 25.35 x 17.65 mm)

Weight** 0.8 oz (23 g)

Power 3.3 V low power consumption

Certification FCC Class B, CE Class B

Operating Temp.

32 to 158°F (0 to 70°C)

Storage Temp. 32 to 158°F (0 to 70°C)

Operating Humidity 10 to 90% Noncondensing

Storage Humidity 10 to 90% Noncondensing

* With cap removed and cable fully extended ** With cap attached Visit <u>linksys.com/support</u> for award-winning technical support

© 2014 Belkin International, Inc. and/or its affiliates. All rights reserved. BELKIN, UNKSYS and many product names and logos are trademarks of the Belkin group of companies. Third-party trademarks mentioned are the property of their respective owners.

LNKPG-00103 Rev. A01