



# 8623 Staticide® Flux Remover No Clean

## Powerful solvent for rosin and no-clean flux removal

Flux Remover No Clean is a powerful solvent that removes substantial baked-on flux deposits resulting from no-clean soldering applications. This super-strength cleaner penetrates rapidly into hard-to-reach areas and will evaporate quickly without leaving residues.

Use the brush applicator for the removal of heavy soils. Test product for compatibility on plastic prior to use.

### Ideal for the following applications:

- Removes R, RA, RMA, and all no-clean flux residues
- Cleans flux residues from PCBs, plugs, sockets, metal housings, motors, generators, heat sinks, ship carriers, relays, contacts, solenoids, switches, surface mount devices, and pads.

### Features:

- ❖ Flammable
- ❖ Test on plastics
- ❖ Non-corrosive and safe for metals
- ❖ Evaporates quickly without leaving residue
- ❖ Low odor
- ❖ Penetrates challenging-to-reach areas
- ❖ Removes encrusted dirt, grease and other contaminants
- ❖ RoHS compliant
- ❖ No CFCs, HCFCs, or 1,1,1 Trichloroethane
- ❖ VOC: CARB 59%
- ❖ Made in USA

### Directions:

To clean, spray surface from a distance of 4-6 inches. Apply cleaner from top to bottom, allowing liquid to flush away flux residues, dirt, and oil. Use extension brush for the removal of encrusted residuals. Special valve allows for 360° spraying.

For industrial use only.  
Read MSDS carefully prior to use.

### Material Compatibility:

ABS	Poor
Buna-N	Poor
EPDM	Good
Graphite	Good
HDPE	Good
Kynar™	Good
LDPE	Good
Lexan™	Poor
Neoprene	Fair
Noryl	Poor
Nylon™ 66	Good
Cross-linked PE	Good
Polypropylene	Good
Polystyrene	Poor
PVC	Poor
Silicone Rubber	Poor
Teflon™	Good
Viton™	Poor

### Product# 8623

12 oz (340g) aerosol / 12 per case