

# IFI23 - 3 STAGE MAINS CONDITIONER & FILTER SC 5690

The IFI23 has three stages for the individual who requires that extra level of coverage.

Technical Specifications (typical figures)

**Three stage Filter (Model IFI-23) Colour-Brushed Silver**

Insertion Loss dB

150 kHz. 58

3MHz. 80

30 MHz. 55

1 GHz. 22

**Operating Voltage** 220-250V ac

**Max Current rating** 13A

**Max Surge Protection** L-N 6500A, L-E 6500A, N-E 6500A

**Max Voltage Spike Protection** 6,000 Volts

**No Neon Indicator** These can inject noise into your Hi-Fi and effect the sound quality

**Mains Lead** Our superior mains cable uses multi layer screening to help provide protection against radiated outside interference.

1.5mm sq 3 core mains cable oversheathed in VN207/2 clear PVC

Incorporating, Melinex tape, Aluminium Foil Screen and Tinned Copper cross hatch braiding.

*The Tacima Mains Conditioner is ideal for use with the following products:*

**CD • Home Cinema • Turntable • Tuner**

**Amp • DVD • & much much more**



CE



*Six device capacity on rear*