




Protection to IP20 Dims: to DIN 43880 W. 17.5mm

- *NEW* 17.5mm DIN rail housing
- □ Switch Initiated Delay Off (Delay On Release) re-triggerable timing function
- 7 Selectable time ranges (0.1 seconds 100 hours)
- Fine adjustment of selected time range
- Multi-voltage input (12 230V AC/DC)
 - External trigger input can be from Voltage Free Contact or Solid State
- □ Timer will still function with load connected to trigger (B1) input
- 1 x SPDT relay output 8A
- Green LED indication for supply / timing status
- Red LED indication for relay status
- Conforms to IEC 61812

Supply A1, A2 V.F.C. A1, B1 O O Output 15-0-16 LED operation: LED operation:

INSTALLATION AND SETTING



- BEFORE INSTALLATION, ISOLATE THE SUPPLY.
- Connect the unit as required.

Settina the unit

- Set the "Range" 1 to the required position (depending on whether seconds, minutes or hours are required).

Annlying nower


- Apply power across terminals A1 and A2 and the green LED will illuminate.
- The relay will remain de-energised (contacts 15 / 16 closed and 15 / 18 open) and red LED @ extinguished.
- Close the contact across A1 and B1 and the relay will energise (contacts 15 / 16 open and 15 / 18 closed) and red LED illuminate.
- When the contact across A1 and B1 opens, the delay period "t" will begin and the green LED will
 flash to indicate timing is now in progress.
- After the delay period "t" has elapsed, the relay will de-energise (contacts 15 / 16 closed and 15 / 18 open) and the red LED will extinguish.
- The green LED will now remain permanently lit.
- The whole timing process is repeated by removing and re-applying power.
- If during the time period "t", the contact across A1 and B1 closes, timing will stop and restart
 over again the next time the contact opens.

Note:

 1 In accordance with IEC 61812, the green LED is permitted to extinguish during a voltage dip or momentary interruption of the power supply providing the state of the output relay does not change. The dip / interruption duration and levels are defined in the product standard.

TECHNICAL SPECIFICATION Supply voltage U (A1, A2): 12 - 230V AC/DC 48 - 63Hz (AC supplies) Frequency range Supply variation +/ - 15% III (IFC 60664) Overvoltage category: Rated impulse withstand voltage 4kV (1.2/50μS) IEC 60664 Power consumption (max.): 12V 24V 110V 230V 0.4VA AC. 0.3VA 1.3VA 3.4VA 0.26W 0.24W 0.95W Timing function: Switch Initiated Delay Off Timing ranges (7): Seconds: Minutes Hours: 0.1 – 1 0.1 – 1 0.1 - 11-10 1 - 101 - 1010 - 100 Reset time: 100mS ± 1% of maximum full scale Accuracy: Adjustment accuracy < 5% of maximum full scale Repeat accuracy: $\pm\,0.5\%$ at constant conditions (IEC 61812) ±0.05% / °C Drift with temperature ± 0.2% / V Drift with voltage External trigger input (A1 > B1): Volt Free Contact, Open Collector Yes, between B1 and A2 (i.e. LED, Relay, Lamp) External loading: Trigger threshold: >75% of voltage present between A1 and A2 (auto-set) Minimum trigger time: AC: 60mS DC: 40mS (B1 terminal unloaded) Maximum input frequency: 10 Hz (with 50:50 duty cycle) Maximum cable length: 10m (between Timer and external switching device) Power on indication / Timing1: Green LED Red LFD Relay status Ambient temp: -20 to +60°C Relative humidity +95% Output (15, 16, 18): SPDT relay Output rating AC1 250V 8A (2000VA) AC15 250V 5A (no), 3A (nc) DC1 25V 8A (200W) Electrical life: ≥ 150,000 ops at rated load 2kV AC (rms) IEC 60947-1 Dielectric voltage: Rated impulse withstand voltag 4kV (1.2/50µS) IEC 60664 Orange flame retardant UL94 Housing Weight: ≈ 60g Mounting option: On to 35mm symmetric DIN rail to BS EN 60715 or direct surface mounting via 2 x M3.5 or 4BA screws using the black clips provided on the rear of the unit. Terminal conductor size \leq 2 x 2.5mm 2 solid or stranded Approvals: Conforms to IEC 61812. CE, C-tick Cand RoHS Compliant. EMC: Immunity: EN 61000-6-2 (EN 61000-4-3 10V/m 80MHz - 2.7GHz) Emissions: EN 61000-6-4

CONNECTION DIAGRAM N/-ve Supply A A1 B1 L/-4-ve External Cap (25) Ex



SETTING DETAILS

1. Power supply status / Timing (Green) LED 2. Relay output status (Red) LED 3. "Set %" adjustment 4. Time delay "Range"

selector

