



FEATURES

- UL 60950 recognition pending
- Single Isolated output
- 1kVDC or 3kVDC option 'Hi Pot Test'
- Wide temperature performance at full 1W load -40°C to 85°C³
- Industry Standard Pinout
- 3.3V, 5V, 12V & 24V Inputs
- 5V, 12V & 15V outputs
- Pin Compatible with CME, CRL2, LME, MEE1, MEE3, MTE1, NKE, NME, NML & NTE series
- Through hole and surface mount options available

PRODUCT OVERVIEW

The CRE1 series are a cost effective 1W DC/DC converter series, in industry standard packages with industry standard pinout. Popular input and output voltages are available. The galvanic isolation allows the device to be configured to provide an isolated negative rail in systems where only positive rails exist. The wide temperature range guarantees startup from -40° C and full 1 watt output at 85° C³.

Isolated 1W Single Output Isolated DC/DC Converters

CRE1 Series

rrder Code ¹	Nominal Input Voltage	Output Voltage	Output Current	Load Regulatio		Input Current at Rated Load		EIIIMEIIN	Isolation Capacitance	MTTF ²				
0	٧	V	mA	9, Tura	6 Max	mV	р-р	mA	9 Min	6 Turn	pF	MIL.	Tel.	
CDE120505DC	5	5	200	19p.	14	19p.	10 IVIAX.	206	IVIIII.	Typ.	20	KI	115	
CRE1S0505050	5	5	200	12	14	16	40	286	65	70	30			
CRE1S0515SC	5	15	67	6	7.5	10	25	250	77	80	40			
CRE1S1205SC	12	5	200	8	10	12	30	117	68	71	33			
CRE1S1212SC	12	12	83	4	5	8	20	104	75	80	55			
CRE1S2405SC	24	5	200	8.5	10	13	30	58	67	71	40			
CRE1S2412SC	24	12	83	3	4	10	25	52	75	80	78			
				3KVI	DC isola	ation op	otions							
CRE1S0305S3C	3.3	5	200	10	12	15	25	400	72	75	35			
CRE1S0505S3C	5	5	200	6	8	15	25	250	73	11	24			
	E	5	200	501 10.0		Sunt op	TIONS	204		60	25	6057		
CRE150505MEC	5	5	200	6.5	15	25	00 70	294	70	82	22	30/1		
ONETOODONNEO	5	0	200	0.5	0	23	10	200	15	02	LL	5041		
INPUT CHARAC	TERIS	TICS								-				
Parameter		Cond	itions					Min		Гур.	Max.	l	Inits	
		Conti	nuous	operatio	on, 3.3V	/ input t	ypes	2.97	, 	3.3	3.63	_	V	
Voltage range		Conti	Continuous operation, 5V input types					4.5	,	5.0	5.5			
		Conti	Continuous operation, 12V Input types						0 12 6 24		13.2			
		2 21/	110005 (8. 19\/ i	operation	JII, 24V	input ty	pes	21.0)	24 1	20.4			
		5V &	5.3v & 12v Input types							2	15	_	_	
Reflected ripple cu	irrent	CRF1	CBF1S0505MC							30	47	— m	mA p-p	
		CRE1	CRE1S0505MEC							5	15			
	OTEDI	etice												
Doremotor	GIENI	Conc	litione					Min	-	Typ	Max		Inite	
Rated Power		T	$a = -40^{\circ}$ C to 85° C ³					IVIIII	•	тур.	1 IVIAN.	W		
Voltage Set Point A	Accurac	v See t	See tolerance envelope											
Line regulation	10001100	High	High Vin to low Vin							1.1	1.2	C	%/%	
	рлети	DIGTIC	e											
Parameter	INAU TI	Conc	• litions					Mi	n	Typ	Max		Inite	
rarameter		C Ver	/ersions Flash tested for 1 second					100	00	iyp.	IVIUN		/111.3	
Isolation test volta	ge	3C Ve	ersions Flash tested for 1 second					3000				VDC		
Resistance Viso=		= 1000	1000VDC						10			GΩ		
GENERAL CHAR	ACTE	RISTICS												
Parameter			Con	ditions				Mir	1.	Тур.	Мах	. l	Jnits	
			3.3	input 1	ypes					115				
			5V ir	nput typ	Des					110		kHz		
Switching frequen	су		12V	input ty	ypes					145				
			24V	input ty	/pes					100				
			CRE1S0505MEC							80				

1. If components are required in tape and reel format suffix order code with -R, e.g. CRE1S0505MC-R.

2. Calculated using MIL-HDBK-217 FN2 and Telcordia SR-332 calculation model with nominal input voltage at full load.

3. 24V input parts prior to date code D1635 have operating temperature range of 0 to 70 $^{\circ}\text{C}.$

All specifications typical at TA=25°C, nominal input voltage and rated output current unless otherwise specified.

www.murata-ps.com/support

For full details go to

w.murata-ps.com/rohs

CRE1 Series

Isolated 1W Single Output Isolated DC/DC Converters

ABSOLUTE MAXIMUM RATINGS								
Lead temperature 1.5mm from case for 10 seconds	260°C							
Input voltage VIN, 3.3V input	5.5V							
Input voltage VIN, 5V input	7V							
Input voltage VIN, 12V input	15V							
Input voltage VIN, 24V input	28V							

TEMPERATURE CHARACTERISTICS									
Parameter	Conditions	Min.	Тур.	Max.	Units				
Specification	All output types ¹	-40		85	°C				
Storage		-50		130					
	5V output types			41					
Case temperature rise above	All other output types			32	U				
ambient	CRE1S0505MC		43						
	CRE1S0505MEC		12.5						
Cooling	Free air convection								

TECHNICAL NOTES

ISOLATION VOLTAGE

'Hi Pot Test', 'Flash Tested', 'Withstand Voltage', 'Proof Voltage', 'Dielectric Withstand Voltage' & 'Isolation Test Voltage' are all terms that relate to the same thing, a test voltage, applied for a specified time, across a component designed to provide electrical isolation, to verify the integrity of that isolation.

Murata Power Solutions CRE1 series of DC/DC converters are all 100% production tested at their stated isolation voltage. This is 1kVDC for 1 second for C versions and 3kVDC for 1 second for 3C versions.

A question commonly asked is, "What is the continuous voltage that can be applied across the part in normal operation?"

The CRE1 is pending recognition by Underwriters Laboratory for functional insulation, both input and output should normally be maintained within SELV limits i.e. less than 42.4V peak, or 60VDC. The isolation test voltage represents a measure of immunity to transient voltages and the part should never be used as an element of a safety isolation system. The part could be expected to function correctly with several hundred volts offset applied continuously across the isolation barrier; but then the circuitry on both sides of the barrier must be regarded as operating at an unsafe voltage and further isolation/insulation systems must form a barrier between these circuits and any user-accessible circuitry according to safety standard requirements.

REPEATED HIGH-VOLTAGE ISOLATION TESTING

It is well known that repeated high-voltage isolation testing of a barrier component can actually degrade isolation capability, to a lesser or greater degree depending on materials, construction and environment. The CRE1 series has toroidal isolation transformers, with no additional insulation between primary and secondary windings of enameled wire. While parts can be expected to withstand several times the stated test voltage, the isolation capability does depend on the wire insulation. Any material, including this enamel (typically polyurethane) is susceptible to eventual chemical degradation when subject to very high applied voltages thus implying that the number of tests should be strictly limited. We therefore strongly advise against repeated high voltage isolation testing, but if it is absolutely required, that the voltage be reduced by 20% from specified test voltage.

This consideration equally applies to agency recognized parts rated for better than functional isolation where the wire enamel insulation is always supplemented by a further insulation system of physical spacing or barriers.

SAFETY APPROVAL

The CRE1 series is pending recognition by Underwriters Laboratory (UL) to UL 60950 for functional insulation in a maximum still air ambient temperature of 85°C and/or case temperature limit (case temperature measured on the face opposite the pins).

1. 24V input parts prior to date code D1635 have operating temperature range of 0 to 70°C.

KDC_CRE1.BO2 Page 3 of 14

www.murata-ps.com/support

1. 24V input parts prior to date code D1635 have operating temperature range of 0 to 70°C.

EFFICIENCY VS LOAD 3.3V Inputs **5V Inputs** 80 70 70 60 (%) 50 (%) -CRE1S0505XC 50 Efficiency Efficiency 40 40 30 20 20 10 10 Load (%) Load (%) **12V** Inputs 24V Inputs 90 80 80 70 70 60 60 \$ ₅₀ ê 50 -CRE1S2405S0 CRE181205SC 40 Efficiency Efficiency 40 CRE1S2412SC -CRE1S1212SC 30 30 20 20 10 10 0 0 20 30 50 90 100 0 10 20 50 100 10 60 60 Load (%) Load (%)

TEMPERATURE DERATING GRAPH - Surface Mount & 3C types



muRata Ps Murata Power Solutions

CRE1 Series

CRE1 Series

Isolated 1W Single Output Isolated DC/DC Converters

TOLERANCE ENVELOPES

The voltage tolerance envelope shows typical load regulation characteristics for this product series. The tolerance envelope is the maximum output voltage variation due to changes in output loading.



CRE1 Series

Isolated 1W Single Output Isolated DC/DC Converters



RoHS COMPLIANCE and MSL INFORMATION



The Through Hole parts (SIP/DIP) in this series are compatible with RoHS soldering systems with a peak wave solder temperature of 260°C for 10 seconds. The pin termination finish on the SIP package type is Tin Plate, Hot Dipped over Matte Tin with Nickel Preplate. The DIP types are Matte Tin over Nickel Preplate. This series is backward compatible with Sn/Pb soldering systems.

The Surface Mount parts (MC/MEC) in this series are compatible with RoHS soldering systems as per J-STD-020D.1 The pin termination finish on the Surface Mount package types is Matte Tin over Bickel Preplate. This series is backward compatible with Sn/Pb soldering systems. The Surface Mount parts have a Moisture Sensitivity Level (MSL) 1.

Samples of the Surface Mount parts were tested in accordance with the conditioning described for MSL level 1 in IDC/J-STD-020D.1. The products passed electrical tests and visual inspection criteria.

For further information, please visit www.murata-ps.com/rohs

CRE1 Series

Isolated 1W Single Output Isolated DC/DC Converters

APPLICATION NOTES

Minimum load

The minimum load to meet datasheet specification is 10% of the full rated load across the specified input voltage range. Lower than 10% minimum loading will result in an increase in output voltage, which may rise to typically double the specified output voltage if the output load falls to less than 5%.

Capacitive loading and start up

Typical start up times for this series, with a typical input voltage rise time of 2.2 μ s and output capacitance of 10 μ F, are shown in the table below. The product series will start into a capacitance of 47 μ F with an increased start time, however, the maximum recommended output capacitance is 10 μ F.

	Start-up time			-	Туріс	cal S	tart	-Up	Wav	e For	m		
	μs						<u>۔</u>						
CRE1S0505DC	190	1+	-				Ţ				: fariant		
CRE1S0505SC	190												
CRE1S0515SC	1790		-				[
CRE1S1205SC	125			2	1								
CRE1S1212SC	500			-	-								
CRE1S2405SC	135			j	ψū	ιįπ					j	ιiπ	÷
CRE1S2412SC	430		-								÷		
CRE1S0305S3C	295		-					1					
CRE1S0505S3C	165						•••	1					
CRE1S0505MC	1368	2*				-	4	()					
CRE1S0505MEC	170		-										

CRE1 Series

Isolated 1W Single Output Isolated DC/DC Converters

APPLICATION NOTES (continued)

Ripple & Noise Characterisation Method

Ripple and noise measurements are performed with the following test configuration.

C1	1 µF X7R multilayer ceramic capacitor, voltage rating to be a minimum of 3 times the output voltage of the DC/DC converter
C2	10μ F tantalum capacitor, voltage rating to be a minimum of 1.5 times the output voltage of the DC/DC converter with an ESR of less than $100m\Omega$ at 100 kHz
C3	100nF multilayer ceramic capacitor, general purpose
R1	450 Ω resistor, carbon film, ±1% tolerance
R2	50Ω BNC termination
T1	3T of the coax cable through a ferrite toroid
RLOAD	Resistive load to the maximum power rating of the DC/DC converter. Connections should be made via twisted wires
Measured value	ues are multiplied by 10 to obtain the specified values.

Differential Mode Noise Test Schematic



Output Ripple Reduction

By using the values of inductance and capacitance stated, the output ripple at the rated load is lowered to 5mV p-p max.

Component selection

Capacitor: It is required that the ESR (Equivalent Series Resistance) should be as low as possible, ceramic types are recommended. The voltage rating should be at least twice (except for 15V output), the rated output voltage of the DC/DC converter.

Inductor: The rated current of the inductor should not be less than that of the output of the DC/DC converter. At the rated current, the DC resistance of the inductor should be such that the voltage drop across the inductor is <2% of the rated voltage of the DC/DC converter. The SRF (Self Resonant Frequency) should be >20MHz.



		Inductor				
	L, µH	SMD	Through Hole	C, μF		
CRE1S0505DC						
CRE1S0505SC						
CRE1S0515SC						
CRE1S1205SC						
CRE1S1212SC						
CRE1S2405SC						
CRE1S2412SC						
CRE1S0305S3C						
CRE1S0505S3C						
CRE1S0505MC	47	82473C	11R473C	4.7		
CRE1S0505MEC	10	82103C	11R103C	4.7		

CRE1 Series

Isolated 1W Single Output Isolated DC/DC Converters

EMC FILTERING AND SPECTRA

FILTERING

The following table shows the additional input capacitor and input inductor typically required to meet EN 55022 Curve B Quasi-Peak EMC limit, as shown in the following plots. The following plots show positive and negative quasi peak and CISPR22 Average Limit B (pink line) and Quasi Peak Limit B (green line) adherence limits. The recommended input capacitor to use for this circuit is 50V 16V X7R ceramic capacitor. For the CRE1S0505MEC an input inductor is not required.



		Capacitor		
Part Number	L, μΗ	SMD	Through Hole	C, μF
CRE1S0505DC	4.7	82472C	13R472C	4.7
CRE1S0505SC	4.7	82472C	13R472C	4.7
CRE1S0515SC	4.7	82472C	13R472C	4.7
CRE1S1205SC	10	82103C	13R103C	1
CRE1S1212SC	10	82103C	13R103C	1
CRE1S2405SC	22	82223C	13R223C	10
CRE1S2412SC	22	82223C	13R223C	10
CRE1S0305S3C	10	82103C	13R103C	1
CRE1S0505S3C	10	82103C	13R103C	1
CRE1S0505MC	10	82103C	13R103C	4.7
CRE1S0505MEC	N/A	N/A	N/A	22



CRE1 Series

Isolated 1W Single Output Isolated DC/DC Converters



www.murata-ps.com/support

KDC_CRE1.BO2 Page 9 of 14

CRE1 Series



CRE1 Series



CRE1 Series

Isolated 1W Single Output Isolated DC/DC Converters



www.murata-ps.com/support

KDC_CRE1.B02 Page 12 of 14

CRE1 Series



CRE1 Series

Isolated 1W Single Output Isolated DC/DC Converters



Murata Power Solutions, Inc. 11 Cabot Boulevard, Mansfield, MA 02048-1151 U.S.A. ISO 9001 and 14001 REGISTERED



and the Life and Safety Critical Application Sales Policy: Refer to: http://www.murata-ps.com/requirements/

Murata Power Solutions, Inc. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Specifications are subject to change without notice.