

DC Power Supply



Description

Has a master-slave tracking, constant voltage, constant current function. The main outputs can be connected in parallel or in series, voltage regulator, steady flow automatically converted, the state will not use any external damage.

Features

- Triple Output
- Series or Parallel Operation
- Current Limitation
- Auto switching between voltage and current operation

Specifications

Output Voltage	CH1, CH2	0 to 24V
	CH3	5V
Output Current	CH1, CH2	0 to 1A
	CH3	2A
Overload Effect	CV $\leq 1 \times 10^{-4} + 2\text{mV}$, CC $\leq 20\text{mA}$	
Ripple & Noise	CV $\leq 1\text{mVrms}$, CC $\leq 1\text{mArms}$	
Regulation	CV : 20mV (Typical), CC : 50mA (Typical)	
Mutual Effect	CV : $5 \times 10^{-5} + 1\text{mV}$, CC : $< 0.5\text{mA}$	
Tracking Error	$5 \times 10^{-3} + 2\text{mV}$	
Indication Method	Digital LED display, also shows the voltage and current values	
Reliability	MTBF (e) : $\geq 2,000$ hours	

General Characteristics

Power	220V $\pm 10\%$, 50Hz $\pm 4\%$
Product Colour	White and Grey
Working Environment	0°C to +40°C, -5°C to +40°C
Product Net Weight	4 kg
Product Size (W×H×D)	210mm × 152mm × 305mm
Standard Accessories	Power cord

Part Number Table

Description	Part Number
Power Supply, 3CH, 24V, 2A, Adjustable	72-8335A

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.

