

SENNHEISER AB 3 ANTENNA BOOSTER



Antenna booster

With a 42 MHz switching bandwidth and 10 dB amplification, this antenna booster is designed for the upgraded performance characteristics of ew G3 receivers. Up to two AB 3 boosters for each antenna feed can compensate for RF losses through remote antenna cables. Power is supplied to the boosters over the ASA 1/NT 1-1 through the BNC cable.

Technical Data

Switching bandwidth : 42 MHz
RF frequency range : 516 865 MHz
Gain : > 10 dB
Antenna connector : BNC
Impedance : 50 Ohm
Dimensions : 95 x 47 x 21 mm
Weight : 60 g

Variants

74-4474	SENNHEISER 502567 AB 3-A ANTENNA BOOSTER	(516-558MHz)
74-4475	SENNHEISER 502572 AB 3-G ANTENNA BOOSTER	(566-608 MHz)
74-4476	SENNHEISER 502568 AB 3-B ANTENNA BOOSTER	(626-668 MHz)
74-4477	SENNHEISER 502569 AB 3-C ANTENNA BOOSTER	(734-776MHz)
74-4478	SENNHEISER 502570 AB 3-D ANTENNA BOOSTER	(780-822 MHz)
74-4479	SENNHEISER 502571 AB 3-E ANTENNA BOOSTER	(823-865 MHz)
NSR-10565	SENNHEISER 504680 AB 3-GB ANTENNA BOOSTER	(606-648 MHz)