



Part Number: QUICK854

Description: Infrared Preheater



Features:

- Imported infrared ceramic heater, fast heating, high efficiency, long life time.
- Built-in thermometer, can check temperature of PCB conveniently.
- Closed-loop sensor, PID control, temperature accurate and stable.
- Suitable for PCB preheating and other process which requires whole and even heating.

Specifications:

Power Consumption	400 W
Heating Area	130×130mm
Plate Material	Ceramic heater
Temperature Sensor	K-type thermocouple
Temperature Range	50°C-350°C
Range of Thermometer	0-600°C
Ambient Conditions	0-40°C
Temperature Stability	±1°C
Dimensions	255(L)×200(W)×63(H)mm
Weight	About 2.5kg