

XF9F1851

overtravel power limit switch - manual reset - 3P -
185 A - 3P scheme



Main

Range of product	XR and XF
Product or component type	Overtravel limit switches
Device short name	XF9
Electrical circuit type	Power circuit
Product specific application	Safety of hoisting equipment
Material	Sheet steel (enclosure)
Type of operator	Manual latching
Number of poles	3
[Ie] rated operational current	AC-3, Ie = 185 A) 3-pole scheme

Complementary

Reset	Manual reset
Switch actuation	Horizontal and vertical approach
Contacts type and composition	Without auxiliary contact block
Contact operation	Snap action
[Ithe] conventional enclosed thermal current	275 A at -25...40 °C 3-pole scheme
[Ui] rated insulation voltage	660 V conforming to IEC 158-1 660 V conforming to IEC 947-4 660 V conforming to VDE 0110 group C 600 V conforming to CSA C22.2 No 14
Rated breaking capacity	1200 kA at 660 V 2-pole scheme conforming to IEC 158-1 1600 kA at 500 V 2-pole scheme conforming to IEC 158-1
Cable cross section	1 solid cable 150 mm ² with cable end 2 solid cable 150 mm ² with cable end
Cable entry	2 entries tapped for Pg 36 cable gland
Product weight	27.5 kg

Environment

standards	IEC 158-1 IEC 947-1 IEC 947-4 NF C 63-110 VDE 0660
product certifications	CSA
protective treatment	TC
ambient air temperature for operation	-25...70 °C
ambient air temperature for storage	-40...70 °C
IP degree of protection	IP43 conforming to EN/IEC 60529

Offer Sustainability

Sustainable offer status	Not Green Premium product
RoHS (date code: YYWW)	Will be Compliant on 4Q2014 Will be Compliant on 4Q2014

Contractual warranty

Warranty period	18 months
-----------------	-----------

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.