

PRODUCT-DETAILS

E3N/MS32004pWMPnew

E3N/MS 3200 4p W MP new



General Information

Extended Product Type	E3N/MS32004pWMPnew
Product ID	1SDA058992R1
EAN	8015644613518
Catalog Description	E3N/MS 3200 4p W MP new
Long Description	SACE EMAX MOVING PART FOR C.BREAKER SWITCH-DISCONNECTOR E3N/MS 3200A FOUR-POLE NEW

Ordering

EAN	8015644613518
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

Dimensions

Product Net Width	558 mm
Product Net Height	461 mm
Product Net Depth / Length	396.5 mm
Product Net Weight	81 kg

Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	515 mm
Package Level 1 Height	600 mm
Package Level 1 Depth / Length	785 mm
Package Level 1 Gross Weight	96 kg
Package Level 1 EAN	8015644609139

Additional Information

Current Type	AC
Electrical Durability	6000 cycle 20 cycles per hour
Mechanical Durability	20000 cycle 60 cycles per hour
Number of Poles	4
Power Loss	570 W
Product Main Type	SACE Emax
Product Name	Switch Disconnecter
Product Type	Air Circuit Breaker
Rated Current (I_n)	3200 A
Rated Voltage (U_r)	690 V
Rated Impulse Withstand Voltage (U_{imp})	12 kV
Rated Insulation Voltage (U_i)	1000 V
Rated Operational Current (I_e)	3200 A
Rated Operational Voltage	690 V AC 250 V DC
Rated Short-time Withstand Current (I_{cw})	for 1 s 65 kA for 3 s 65 kA
Rated Uninterrupted Current (I_u)	3200 A
Standards	IEC
Sub-type	E3
Terminal Connection Type	Withdrawable Circuit-Breakers
Version	W

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200006D0209
Declaration of Conformity - CE	1SDL000165R0015
Environmental Information	1SDL000142R0
Instructions and Manuals	1SDH000460R0002

Classifications

ETIM 4	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 5	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 6	EC000216 - Switch disconnecter
Object Classification Code	Q

WEEE Category

4. Large Equipment (Any External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax

