



**DFROBOT**<sup>®</sup>  
DRIVE THE FUTURE

# Bluno Nano - Arduino Nano Compatible - Bluetooth 4.0

SKU:DFR0296



## INTRODUCTION

Here comes the second member in the [DFRobot Bluno family](#), the Bluno Nano. Came in the size of a gum, the Bluno Nano is perfect for [BLE projects](#) with limited space or weight. You may also check the [Bluetooth microcontroller selection guide](#) to get more information.

Everything is getting smart now: wristbands and watches monitor your daily behaviors and become social; phone-controlled camera add-ons move and take shots as you like; smart gardens grow virtually in your iPad and sharing is made easy... The Bluetooth Low Energy technology has made it easy and achievable. It is exciting to see more and more smart gadgets popping out, but, isn't building own smart device and solving your own problems even cooler?

DFRobot's Bluno family is the first of its kind in integrating BT 4.0(BLE) module into "Arduino Uno", making it an ideal prototyping platform for developers to go [wireless](#). You will be able to develop your own smart bracelet, smart pedometer, and more. Through the low-power [Bluetooth 4.0 technology](#), real-time low energy communication can be made really easy.



**DFROBOT**<sup>®</sup>  
DRIVE THE FUTURE

Bluno Nano also integrates a TI CC2540 BT 4.0 chip with the "Arduino UNO" development board. It allows wireless programming via BLE, supports Bluetooth HID, supports AT command to config the BLE, and you can upgrade BLE firmware easily. Bluno is also compatible with all Arduino Uno pins which means any project made with Uno can directly go wireless! Whatsmore, we also developed the App for the Bluno (both Android and IOS), and they are completely open-source so that you can modify and develop your own hardware-software platform.

**Note: For expanding I/O ports, the Bluno Nano is compatible with all Arduino-Nano-compatible expansion shields. If you want to use Bluno Nano via other expansion shields, some extra wirings will be needed.**

## *SPECIFICATION*

- On-board BLE chip: TI CC2540
- Wireless Programming Via BLE
- Support Bluetooth HID
- Support AT command to config the BLE
- Transparent communication through Serial
- Upgrade BLE firmware easily
- DC Supply: USB Powered or External 7V~12V DC
- Microcontroller: Atmega328
- Bootloader: Arduino Uno
- Compatible with the Arduino Uno pin mapping
- Size: 53x19x12mm(2.09x0.75x0.47")
- Weight: 20g