DATASHEET - P5-125/E

On-Off switch, P5, 125 A, flush mounting, 3 pole, with black thumb grip and front plate



Part no. P5-125/E 280897

General specifications	
Product name	Eaton Moeller® series P5 On-Off switch
Part no.	P5-125/E
EAN	4015082808976
Product Length/Depth	90 millimetre
Product height	140 millimetre
Product width	100 millimetre
Product weight	1.128 kilogram
Compliances	CE Marked
Certifications	UL 508 IEC 60947 EN 60947-3 CSA Std. C22.2 No. 14-05 VDE IEC/EN 60947 VDE 0660 CSA-C22.2 No. 94 UL File No.: E36332 CSA Class No.: 3211-05 IEC/EN 60204 CSA UL Category Control No.: NLRV CE CSA-C22.2 No. 14-05 IEC/EN 60947-3 UL CSA File No.: 223805
Product Tradename	P5
Product Type	On-Off switch
Product Sub Type	None
Catalog Notes	Rated Short-time Withstand Current (Icw) for a time of 1 second
Features & Functions	
Fitted with:	Black thumb grip and front plate
Number of poles	3
General information	
Accessories	Auxiliary contact or neutral conductor fitted by user.
Degree of protection	NEMA 12
Degree of protection (front side)	IP65
Lifespan, mechanical	100,000 Operations
Mounting method	Flush mounting
Mounting position	As required
Operating frequency	50 Operations/h
Overvoltage category	
Pollution degree	3
Rated impulse withstand voltage (Uimp)	8000 V AC
Safe isolation	440 V AC, Between the contacts, According to EN 61140
Safety parameter (EN ISO 13849-1)	B10d values as per EN ISO 13849-1, table C.1
Suitable for	Front mounting 4-hole Branch circuits, suitable as motor disconnect, (UL/CSA)
Climatic environmental conditions	
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	50 °C
Ambient operating temperature (enclosed) - min	-25 °C
Ambient operating temperature (enclosed) - max	40 °C
Climatic proofing	Damp heat, cyclic, to IEC 60068-2-30

	Damp heat, constant, to IEC 60068-2-78
Terminal capacities	
Terminal capacity	2 x 35 mm ² , solid or stranded 2/0 AWG, flexible 1 x 70 mm ² , flexible with ferrules to DIN 46228 3/0 AWG, solid or flexible conductor with ferrule 2 x 25 mm ² , flexible with ferrules to DIN 46228 1 x 95 mm ² , solid or stranded 2 x 13 x 1.5 mm Number of segments x width x thickness, copper strip 1 x 13 x 3 mm Number of segments x width x thickness, copper strip
Screw size	5 mm AF, Hexagon socket-head spanner, Terminal screw
Tightening torque	14 Nm, Screw terminals 125 Ib-in, Screw terminals
Electrical rating	
Rated breaking capacity at 220/230 V (cos phi to IEC 60947-3)	800 A
Rated breaking capacity at 400/415 V (cos phi to IEC 60947-3)	750 A
Rated breaking capacity at 500 V (cos phi to IEC 60947-3)	650 A
Rated breaking capacity at 660/690 V (cos phi to IEC 60947-3)	340 A
Rated operational current (Ie) at AC-3, 220 V, 230 V, 240 V	72 A
Rated operational current (Ie) at AC-3, 380 V, 400 V, 415 V	66 A
Rated operational current (Ie) at AC-3, 500 V	58 A
Rated operational current (Ie) at AC-3, 660 V, 690 V	32 A
Rated operational current (Ie) at AC-21, 440 V	125 A
Rated operational current (Ie) at AC-23A, 230 V	96 A
Rated operational current (Ie) at AC-23A, 400 V, 415 V	80 A
Rated operational current (Ie) at AC-23A, 500 V	78 A
Rated operational current (Ie) at AC-23A, 690 V	39 A
Rated operational current (Ie) at DC-1, load-break switches $I/r = 1 ms$	125 A
Rated operational current (Ie) at DC-23A, 24 V	125 A
Rated operational current (Ie) at DC-23A, 48 V	125 A
Rated operational current (Ie) at DC-23A, 60 V	125 A
Rated operational current (Ie) at DC-23A, 120 V	40 A
Rated operational power at AC-3, 380/400 V, 50 Hz	37 kW
Rated operational power at AC-3, 415 V, 50 Hz	37 kW
Rated operational power at AC-3, 500 V, 50 Hz	45 kW
Rated operational power at AC-3, 690 V, 50 Hz	30 kW
Rated operational power at AC-23A, 220/230 V, 50 Hz	30 kW
Rated operational power at AC-23A, 400 V, 50 Hz	45 kW
Rated operational power at AC-23A, 500 V, 50 Hz	55 kW
Rated operational power at AC-23A, 690 V, 50 Hz	37 kW
Rated operational voltage (Ue) at AC - max	690 V
Rated uninterrupted current (lu)	125 A
Uninterrupted current	Rated uninterrupted current lu is specified for max. cross-section.
Short-circuit rating	
Rated conditional short-circuit current (Iq)	30 kA
Rated short-time withstand current (Icw)	2.5 kA 2,5 kA, Contacts, 1 second
Short-circuit current rating (basic rating)	10 kA, SCCR (UL/CSA) 350A Class RK1, max. Fuse, SCCR (UL/CSA)
Short-circuit current rating (high fault)	300 A, Class J, max. Fuse, SCCR (UL/CSA) 65 kA, SCCR (UL/CSA)
Short-circuit protection rating	125 A gG/gL, Fuse, Contacts
Switching capacity	
Load rating	1.3 x I# (with intermittent operation class 12, 60 % duty factor) 2 x I# (with intermittent operation class 12, 25 % duty factor) 1.6 x I# (with intermittent operation class 12, 40 % duty factor)
Number of contacts in series at DC-23A, 24 V	3
Number of contacts in series at DC-23A, 48 V	3
Number of contacts in series at DC-23A, 60 V	3
Number of contacts in series at DC-23A, 120 V	3

Sorticle casary luminary contract, plant any Sorticle casary luminary contract, plant any sorticle casary luminary contract, plant any Mater analy contract, plant any Number of casary luminary of SN 150 pl No FDN 500 pl Plant and SN 200 pl No FDN 500 pl No FDN 500 pl Plant and SN 200 pl No FDN 5	Switching capacity (main contacts, general use)	150 A, Rated uninterrupted current max. (UL/CSA)
Absolution space () usuality construct DCCV (MPT -)ABS (UL CSA)Nulse per construct in write90 AMater or construct in write92 CPAssigned mutric power at 15/100 V (M b, -) thans15 MPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPAssigned mutric power at 15/100 V (M b, -) thans30 PPNationer of thansing vigne contracts90 PNationer of thansi		
Read making expecting up to SSU (reacy that REQPUSED -) SSU - SSU - Water reading CV CV Assigned noter power at 115/120 (K0 Hz, 1-phase SSU - SSU - Assigned noter power at 115/120 (K0 Hz, 1-phase SSU - SSU - Assigned noter power at 115/120 (K0 Hz, 1-phase SSU - SSU - Assigned noter power at 15/120 (K0 Hz, 1-phase SSU - SSU - Assigned noter power at 2020 (K0 Hz, 1-phase SSU - SSU - Assigned noter power at 2020 (K0 Hz, 1-phase SSU - SSU - Assigned noter power at 300 (K0 Hz, 1-phase SSU - SSU - Assigned noter power at 300 (K0 Hz, 1-phase SSU - SSU - Assigned noter power at 300 (K0 Hz, 1-phase SSU - SSU - Number of anxiliary cantacts (normally cantacts) SSU - SSU - Number of anxiliary cantacts (normally cantacts) SSU - SSU - Number of anxiliary cantacts (normally cantacts) SSU - SSU - Number of anxiliary cantacts (normally cantacts) SSU - SSU - Number of anxiliary cantacts (normally cantacts) SSU - SSU -		
Wates per contact par in sense P2 V Mater rating 710 Assigned metra paper at 11510 V, 60 N, 1-phase 7510 Assigned metra paper at 12020 V, 60 N, 5-phase 2000 Assigned metra paper at 12020 V, 60 N, 5-phase 2000 Assigned metra paper at 12020 V, 60 N, 5-phase 2000 Assigned metra paper at 12020 V, 60 N, 5-phase 2000 Assigned metra paper at 12020 V, 60 N, 5-phase 2000 Assigned metra paper at 12020 V, 60 N, 5-phase 2000 Assigned metra paper at 12020 V, 60 N, 5-phase 2000 Assigned metra paper at 12020 V, 60 N, 5-phase 2000 Assigned metra paper at 12020 V, 60 N, 5-phase 2000 Centred circle/bitV 11/law pape per t00.000 perators statistically determed, at 24 V D, 10 Number of auxiliary cantracts (bornally operators statistically determed, at 24 V D, 10 11/law pape to 10.000 perators Actuator type 0 0 Actuator type 2000 V 11/law pape to 10.000 perators Design variations 2000 V 200 V Het dissipation current displation displation file 200 V 200 V 1202 Versitions of auxilians in the dissipation displa		
Action of the power of 15130 (V) 000, 1phose Image of the power of 15130 (V) 000, 2phose Assigned mater power at 12324 (V) 000, 2phose 2109 Assigned mater power at 2324 (V) 000, 2 phose 2109 Assigned mater power at 2324 (V) 000, 2 phose 2109 Assigned mater power at 2324 (V) 000, 2 phose 2109 Assigned mater power at 2324 (V) 000, 2 phose 2009 Assigned mater power at 2324 (V) 000, 2 phose 2009 Assigned mater power at 2324 (V) 000, 2 phose 2009 Assigned mater power at 2324 (V) 000, 2 phose 2009 Assigned mater power at 2324 (V) 000, 2 phose 2009 Assigned mater power at 2324 (V) 000, 2 phose 2000 Assigned mater power at 2324 (V) 000, 2 phose 2000 Assigned mater power at 2324 (V) 000, 2 phose 2400 (P) Assigned mater power at 2324 (V) 000, 2 phose 2400 (P) Matter or anality contracts formally color contracts 0 Number of anality contracts formally color contracts 0 Number of anality contracts formally color contracts 1000 Assist of road mater power at 2324 (V) 000, 2000 1000 Read special contracts formally doning of contracts 1000 <td></td> <td></td>		
Assigned motor power at 118/120 V, 60 Hz, 1 phase Image: 10 Hz P Assigned motor power at 2020 V (V) 00 Hz, 3 phase Image: 10 Hz P Assigned motor power at 2020 V (V) 00 Hz, 3 phase Image: 10 Hz P Assigned motor power at 2020 V (V) 00 Hz, 3 phase Image: 10 Hz P Assigned motor power at 2020 V (V) 00 Hz, 3 phase Image: 10 Hz P Assigned motor power at 2020 V (V) 00 Hz, 3 phase Image: 10 Hz P Assigned motor power at 2020 V (V) 00 Hz, 3 phase Image: 10 Hz P Assigned motor power at 2020 V (V) 00 Hz, 3 phase Image: 10 Hz P Assigned motor power at 2020 V (V) 00 Hz, 3 phase Image: 10 Hz P Assigned motor power at 2020 V (V) 00 Hz, 3 phase Image: 10 Hz P Control circuit mission Image: 10 Hz P Number of anxibiny contracts (homaly coase contracts) Image: 10 Hz P Number of anxibiny contracts (homaly coase contracts) Image: 10 Hz P Actuator color Image: 10 Hz P Actuator color Image: 10 Hz P Actuator color Image: 10 Hz P Parity parity Hz P Image: 10 Hz P Number of anxibing of power the 10 Hz P Image: 10 Hz P Rest displantor, numer and dependent PM Image: 10 Hz P Number of anxibing of ordenarces Image: 10 Hz P Number of anxibing of ordenarces Image: 10 Hz P Number of a		
Assigned motor power at 131210. (40 Hz, 3 phase 16 HP Assigned motor power at 132024. (40 Hz, 1 phase 20 HP Assigned motor power at 232024. (40 Hz, 1 phase 20 HP Assigned motor power at 232024. (40 Hz, 1 phase 20 HP Assigned motor power at 232024. (40 Hz, 1 phase 20 HP Assigned motor power at 232024. (41 Hz, 1 phase 20 HP Assigned motor power at 232024. (41 Hz, 1 phase 20 HP Assigned motor power at 232024. (41 Hz, 1 phase 20 HP Assigned motor power at 232024. (41 Hz, 1 phase 20 HP Assigned motor power at 232024. (41 Hz, 1 phase 20 HP Number of axalitys contracts longinuoup contractal 0 Number of axalitys contracts longinuoup contractal 0 Number of axalitys contracts longinuoup contractal 0 Actuator coror 31 W Actuator toror 31 W Hest dissipation, ser poile, current dependent PA 0W 1022 Draviant motor shall, but dissipation ID 11 W Hest dissipation, or orient dependent PA 0W 1023 Draviant dissipation or orient dependent PA 0W 1024 Draviant contral dependent PA 0W <tr< td=""><td></td><td>7.5 UD</td></tr<>		7.5 UD
Assigned mater power at 230,200 V, 00 Hz, 1-phase 20 HP Assigned mater power at 230,200 V, 00 Hz, 3-phase 30 HP Assigned mater power at 430,400 V, 00 Hz, 3-phase 30 HP Assigned mater power at 430,400 V, 00 Hz, 3-phase 30 HP Assigned mater power at 430,400 V, 00 Hz, 3-phase 30 HP Assigned mater power at 430,400 V, 00 Hz, 3-phase 30 HP Assigned mater power at 430,400 V, 00 Hz, 3-phase 30 HP Assigned mater power at 430,400 V, 00 Hz, 3-phase 30 HP Assigned mater power at 430,400 V, 00 Hz, 3-phase 30 HP Assigned mater power at 430,400 V, 00 Hz, 3-phase 30 HZ Number of auxiliary centexits (normally closet centexits) 30 HZ Number of auxiliary centexits (normally closet centexits) 30 HZ Assignation consult (closet centexits) 30 HZ Heat disaptions consult (closet centexits) 30 HZ Heat disaptions (crimer dispendent Phid 31 W Heat disaptions (crimer dispendent Phid 31 HZ Mater be product stated of requirements. 31 HZ Mater be product stated of requirements. 31 HZ Mater be product stated of requirements. 31 HZ Ma	• • • • • •	
Assigned motor power at 2202-00 V,00 Hz, 3-phase 20 HP Assigned motor power at 25000 V,00 Hz, 3-phase 20 HP Assigned motor power at 55000 V,00 Hz, 3-phase 60 HP Centrate situation of assignary contacts (normally spinsor) 60 HP Number of assignary contacts (normally spinsor) 60 HP Number of assignary contacts (normally spin contacts) 60 HP Number of assignary contacts (normally spin contacts) 60 HP Actuator role 0 Actuator role 31 W Heed displacion capacity Plain 0 Heed displacion capacity Plain 0 Read operational current for specified heat displasion in Projecter displasion projec, current dependent Pvid 123 AP 122.22 Verification of thesis displasion in Projecter displasion projec, current dependent Pvid 124 Heat displacion constrance displasion projec, current dependent Pvid 122.22 Verification of thesis displasion in Projecter displasion projec, current dependent Pvid 125 AP 122.22 Verification of thesis displasion proj		
Assigned motor power at 277 V.0 NV, 1-phase 20 NP Assigned motor power at 277 V.0 NV, 1-phase 20 NP Assigned motor power at 275 V.0 NV, 1-phase 20 NP Control circuit reliability 20 NP Control circuit reliability 1 allor per 100,000 swetching operations statistically determined, st 24 V 00,19 Number of auxiliary contacts (homashy closed contacts) 0 Number of auxiliary contacts (homashy closed contacts) 0 Actuator for 0 Actuator for 0 Actuator for 0 Biging verification 0 Biging verification 0 Number of auxiliary contacts (homashy closed contacts) 0 Heat dissipation, non-current-dependent Pvid 0 Biging verification 0 Biging		
Assigned metry power at 480480 V, DI 42 3 plase Diff Control circuit reliability Failure per 100,000 switching sparators statistically determined, at 24 V DC, 10 Number of auxiliary contracts (change-over contacts) 0 Number of auxiliary contracts (change-over contacts) 0 Number of auxiliary contracts (change-over contacts) 0 Actuator color 0 Actuator color Black Actuator color 31 W Read sparation current-dependent Pvid 00 Read sparation of thread isability of encloarers 11 W Read sparation of thread isability of encloarers 00 Read sparation of thread isability of encloarers 12 SA Read sparation of thread isability of encloarers 12 SA Read sparation of thread isability of encloarers 12 SA Read sparation of thread isability of encloarers 13 W Read sparation of thread isability of encloarers 13 SA Read sparation of thread isability of encloarers 13 SA		
Assigned mater power at 573X00 V, 80 Hz, 3phase 60 HP Contacts 50 HP Contact criss reliability 1 fainer per 100,000 owitching operations statistically determined, at 24 V DC, 10 mAI Number of auxility contacts (longen-over contacts) 0 Number of auxility contacts (longen-over contacts) 0 Number of auxility contacts (longen-over contacts) 0 Actuator over of auxility contacts (longen-over contacts) 0 Actuator role 0 Actuator role 0 Actuator role 0 Actuator role 0 Feed inspiration capacity floss 0 Read dissipation capacity floss 0 Read dissipation, on-current-dependent Pvid 0 Read dissipation on dissipation of resistance 0 102.21 Verification of terminal scholiny of ecclearros 0 102.23 Verification of resistance 0 102.23 Verification of resistance 0 102.24 Verification of resistance		
Contacts Control circuit reliability Islature per 100.000 switching operations statistically determined, at 24 V DC. 10 Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (change-over contacts) 0 Number of auxiliary contacts (change-over contacts) 0 Actuator 0 Actuator 0 Actuator olor 0 Actuator olor 0 Actuator olor 0 Actuator olor 0 Equipment heat dissipation, current dependent Pvid 0 Heat dissipation on paroly Pdiss 0 Heat dissipation, nor current-dependent Pvid 0 Bacta dissipation, nor current-dependent Pvid 0 Build beerational duriner for specified heat dissipation (In) 0 Build beerational fuert for specified heat dissipation (In) 0 Build beerational fuert discret for specified heat dissipation nor current-dependent Pvid 0 Build beerational fuert discret for specified heat dissipation (In) 0 Build beerational fuert discret for specified heat dissipation (In) 0 Build beerational fuert discret for specified heat dissipation (In) 0 <td></td> <td></td>		
Control circuit reliability Infairur per 100,000 switching operations statistically determined, at 24 VD.0.10 Number of auxiliary contacts (hamge-over contacts) 0 Number of auxiliary contacts (hamge-over contacts) 0 Number of auxiliary contacts (hamge-over contacts) 0 Actuator 0 Actuator of over contacts (hormally closed contacts) 0 Actuator of over contacts (hormally contacts) 0 Reliability control dependent Pvid 0 Heat dissipation, current-dependent Pvid 0 Not 22 Verification 125.4 Nortacts (hormally contacts) 102.21 Verification of thermal abability of enclosures 0 102.22 Verification of resistance of nucleon metantisk to normal heat 0 102.22 Verification of resistance of nucleon metantisk to normal heat 0 102.22 Verification of resistance of nucleon metantisk to normal heat 0 102.22 Verification of resistance of nucleon metantisk to normal heat 0 102.22 Verification of resistance of nucleon metantis to norma		
Number of auxiliary contacts (hormally clease contacts) Image of auxiliary contacts (hormally clease contacts) Number of auxiliary contacts (hormally open contacts) Image of auxiliary contacts (hormally open contacts) Actuator Image of auxiliary contacts (hormally open contacts) Actuator color Image of auxiliary contacts (hormally open contacts) Actuator color Image of auxiliary contacts (hormally open contacts) Actuator color Image of auxiliary contacts (hormally open contacts) Actuator color Image of auxiliary contacts (hormally open contacts) Actuator type Image of auxiliary contacts (hormally open contacts) Actuator type Image of auxiliary contacts (hormally open contacts) Actuator type Image of auxiliary contacts (hormally open contacts) Actuator type Image of auxiliary contacts (hormally open contacts) Meat dissipation of contract (dependent Pvid Image of auxiliary contacts (hormally of auxiliary contacts) Image of auxiliary of auxiliary of enclosures Image of auxiliary contact standard's requirements. Image of auxiliary of enclosures Image of auxiliary contact standard's requirements. Image of auxiliary of enclosures Image of auxiliary contact standard's requirements. Image of auxiliary contact standar		1 failure nor 100 000 quitabing appretians statistically datermined at 24 V DC 10
Number of auxiliary contacts from ally open contacts) Image: Contacts from ally open contacts Actuator Image: Contacts from ally open contacts Actuator color Basek Actuator color Basek Actuator type Basek Design verification Image: Contacts from ally open contacts Feature type Image: Contacts from ally open contacts Heat dissipation, capacity Pdiss Image: Contacts from ally open contacts from all open contacts from ally open contacts from all open contacts from ally open contacts from all ope		
Number of auxiliary contacts hormally open contacts) Image: Contact Co		
Actuator Actuator Actuator color Black Actuator yoe Black Design verification Short thumb-gip Design verification 11 W Equipanet that dissipation, current-dependent Pvid 11 W Heat dissipation per pole, current-dependent Pvid 11 W Rate operational current for specification of the specifi		
Actuator color Black Actuator type Short thumb-prip Design verification 31 W Equipment hest dissipation, current-dependent Pvid 31 W Heat dissipation prople, current-dependent Pvid 31 W Rated operational current for specified heat dissipation (In) 125 A 102.21 Verification of thermal stability of enclosures Wests the product standard's requirements. 102.21 Verification of thermal stability of enclosures Meets the product standard's requirements. 102.23 Verification of tresistance of insulating materials to normal heat Meets the product standard's requirements. 102.23 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 102.24 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 102.24 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 102.25 Urification of resistance Meets the product standard's requirements. 102.25 Urification of resistance Meets the product standard's requirements. 102.5 Urification Meets the product standard's requirements. 102.5 Meetion against electric is dock Meets the product standard's requirements. </td <td>Number of auxiliary contacts (normally open contacts)</td> <td>0</td>	Number of auxiliary contacts (normally open contacts)	0
Actuator type Actuator type Actuator type Actuator type Actuator type Design verification Equipment heat dissipation, current-dependent Pvid 3.1 W Heat dissipation capecity Pdss 0W 3.1 W Rated operational current for specified heat dissipation (In) 125 A 125 A 102.2 Corresion resistance 0W 0W 102.3 L Verification of tessification of resistance of insulating materials to normal heat Meets the product standard's requirements. 102.3.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 102.3.2 Nextic final. mat. to abnormal heat/fire by internal elect effects Meets the product standard's requirements. 102.3 Resistance to ultra-violet IUV) radiation Does not apply, since the entire switchpar needs to be evaluated. 102.5 Lifting Does not apply, since the entire switchpar needs to be evaluated. 103.0 Storee of protection of assemblies Does not apply, since the entire switchpar needs to be evaluated. 103.0 Storee of protection of assemblies Does not apply, since the entire switchpar needs to be evaluated. 103.0 Storee of protection of switching devices and components Does not apply, since the entire switchpar needs to be evaluated. 103.0 Internal	Actuator	
Design verification Image: space	Actuator color	Black
Equipment heat dissipation, current-dependent Pvid 3.1 W Heat dissipation capacity Pdiss 0W Rated dissipation, per pole, current-dependent Pvid 3.1 W Rated dissipation, non-current-dependent Pvid 3.1 W Static heat dissipation, non-current-dependent Pvid 0W 10.2.2. Corrison resistance 0W 10.2.2. Corrison resistance 0W 10.2.2. Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3.1 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.4 Resistance to ultra-violet (UV) radiation Meets the product standard's requirements. 10.2.5 Michanical impact Does not apply, since the entire switchgear needs to be evaluated. 10.2.6 Michanical impact Does not apply, since the entire switchgear needs to be evaluated. 10.3 Degree of protection of assemblies Meets the product standard's requirements. 10.4 Retard electric shock Does not apply, since the entire switchgear needs to	Actuator type	Short thumb-grip
Hat dissipation capacity Pdiss Image: Control of the section of the sectin of the section of the section of the secting of the seco	Design verification	
Heat dissipation pr pole, current-dependent Pvid 31 W Rated operational current for specified heat dissipation (In) 125 A Static heat dissipation, non-current-dependent Pvs 0W 10.22 Corrosion resistance 0W 10.22 Corrosion resistance 0W 10.23 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.23 Resist. of insult mit to abnormal heat fire by internal elect effects Meets the product standard's requirements. 10.23 Resist. of insult, mit to abnormal heat fire by internal elect effects Does not apply, since the entire switchgear needs to be evaluated. 10.24 Resistance to ultra-violet (UV) radiation Does not apply, since the entire switchgear needs to be evaluated. 10.25 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.26 Mechanical impact Does not apply, since the entire switchgear needs to be evaluated. 10.27 Inscriptions Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric strength Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9 Thermal electrical circuits and connect	Equipment heat dissipation, current-dependent Pvid	3.1 W
Rated operational current for specified heat dissipation (in) IZSA Static heat dissipation, on-current-dependent Pvs 0W 10.22 Corrosion resistance Meets the product standard's requirements. 10.23.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.23.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.23.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 10.24 Resistance to ultra-wiolet (UV) radiation Meets the product standard's requirements. 10.25 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.25 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies Meets the product standard's requirements. 10.4 Clearances and creepage distances Des not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric shock Des not apply, since the entire switchgear needs to be evaluated. 10.8 Incorporation of switching advices and components Is the panel builder's responsibility. 10.8 Incorporation of switching advices and components Is the panel builder's responsibility. 10.8 Incorporation dis witching advic	Heat dissipation capacity Pdiss	0 W
Static heat dissipation, non-current-dependent Pvs 0 10.22 Corrosion resistance 0 10.23.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.23.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.23.3 Resist of insul. mat. to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 10.24 Resistance to ultra-violet (UV) radiation Meets the product standard's requirements. 10.25 Resist of insul. mat. to abnormal heat/fire by internal elect. effects Does not apply, since the entire switchgear needs to be evaluated. 10.24 Resistance to ultra-violet (UV) radiation Meets the product standard's requirements. 10.25 Resist of insul. mat. to abnormal heat/fire by internal elect. Does not apply, since the entire switchgear needs to be evaluated. 10.27 Internal electrical inpact Does not apply, since the entire switchgear needs to be evaluated. 10.3 Degree of protection of switching devices and components Meets the product standard's requirements. 10.4 Clearances and creepage distances Does not apply, since the entire switchgear needs to be evaluated. 10.4 Thermal electrical forductors Is the panel builder's responsibility. 10.8 Incorporation of switching devices and components	Heat dissipation per pole, current-dependent Pvid	3.1 W
10.22 Corrosion resistanceMeets the product standard's requirements.10.23.1 Verification of thermal stability of enclosuresMeets the product standard's requirements.10.23.2 Verification of resistance of insulating materials to normal heatMeets the product standard's requirements.10.23.3 Resist of insul. mat. to abnormal heat/fire by internal elect. effectsMeets the product standard's requirements.10.24 Resistance to ultra-violet (UV) radiationUV resistance only in connection with protective shield.10.25 LiftingDees not apply, since the entire switchgear needs to be evaluated.10.27 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDees not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesDees not apply, since the entire switchgear needs to be evaluated.10.5 Protection against electric shockDees not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDees not apply, since the entire switchgear needs to be evaluated.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Prover-frequency electric strengthIs the panel builder's responsibility.10.9.3 Inpulse withstand voltageIs the panel builder's responsibility.10.9.1 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the	Rated operational current for specified heat dissipation (In)	125 A
102.3.1 Verification of thermal stability of enclosuresMeets the product standard's requirements.102.3.2 Verification of resistance of insulating materials to normal heatMeets the product standard's requirements.102.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effectsMeets the product standard's requirements.102.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.102.7 InscriptionsDoes not apply, since the entire switchgear needs to be evaluated.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.3 Inpulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionInternal electric devices.10.13 Mechanical	Static heat dissipation, non-current-dependent Pvs	0 W
102.32 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 102.33 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 102.44 Resistance to ultra-violet (UV) radiation UV resistance only in connection with protective shield. 102.55 Lifting Does not apply, since the entire switchgear needs to be evaluated. 102.61 Mechanical impact Does not apply, since the entire switchgear needs to be evaluated. 103.05 Organ of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7.1 Internal electrics for external conductors Is the panel builder's responsibility. 10.8.2 Dower-frequency electric strength Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise Is the panel builder's responsibility. The specifications for the	10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 10.2.4 Resistance to ultra-violet (UV) radiation UV resistance only in connection with protective shield. 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.6 Mechanical impact Does not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions Meets the product standard's requirements. 10.3.8 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4. Clearances and creepage distances Meets the product standard's requirements. 10.5. Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6. Incorporation of switching devices and components Is the panel builder's responsibility. 10.8. Connections for external conductors Is the panel builder's responsibility. 10.8.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise Is the panel builder's responsibility. 10.11 Short-circuit rating Is the panel builder's responsibili	10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
102.4 Resistance to ultra-violet (UV) radiation UV resistance only in connection with protective shield. 102.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 102.6 Mechanical impact Does not apply, since the entire switchgear needs to be evaluated. 102.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility. 10.8.2 Power-frequency electric strength Is the panel builder's responsibility. 10.8.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise Is the panel builder's responsibility. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function Is the pane	10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.	10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.6 Mechanical impactDes not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder 's responsibility.10.10 Temperature riseThe panel builder 's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.2.4 Resistance to ultra-violet (UV) radiation	UV resistance only in connection with protective shield.
10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.10 Temperature rise Is the panel builder's responsibility. 10.11 Short-circuit rating Is the panel builder's responsibility. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provide the information in the instruction	10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.2.7 Inscriptions	Meets the product standard's requirements.
10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.1 Temperature riseIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provide the information in the instruction	10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provide the information in the instruction	10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise Is the panel builder is responsibility. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction		
10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder is responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction		
10.10 Temperature rise The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction		
10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function Image: Compatibility of the switchgear must be observed.		
10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.10 Temperature rise	
10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.11 Short-circuit rating	
	10.12 Electromagnetic compatibility	
	10.13 Mechanical function	

Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / Switch disconnector (EC000216)

Electric engineering, automation, process control engineering / Low-voltage switch [AKF060013])	i technology / C)ff-load sv	vitch, circuit breaker, control switch / Switch disconnector (ecl@ss10.0.1-27-37-14-03
Version as main switch			No
Version as maintenance-/service switch			No
Version as safety switch			No
Version as emergency stop installation			No
Version as reversing switch			No
Number of switches			1
Max. rated operation voltage Ue AC		V	690
Rated operating voltage		V	690 - 690
Rated permanent current lu		А	125
Rated permanent current at AC-23, 400 V		A	125
Rated permanent current at AC-21, 400 V		A	125
Rated operation power at AC-3, 400 V		kW	37
Rated short-time withstand current lcw		kA	2.5
Rated operation power at AC-23, 400 V		kW	45
Switching power at 400 V		kW	45
Conditioned rated short-circuit current Iq		kA	30
Number of poles			3
Number of auxiliary contacts as normally closed contact			0
Number of auxiliary contacts as normally open contact			0
Number of auxiliary contacts as change-over contact			0
Motor drive optional			No
Motor drive integrated			No
Voltage release optional			No
Device construction			Built-in device fixed built-in technique
Suitable for floor mounting			No
Suitable for front mounting 4-hole			Yes
Suitable for front mounting centre			No
Suitable for distribution board installation			No
Suitable for intermediate mounting			No
Colour control element			Black
Type of control element			Short thumb-grip
Interlockable			No
Type of electrical connection of main circuit			Frame clamp
Degree of protection (IP), front side			IP65
Degree of protection (NEMA)			12