

Note: This datasheet may be out of date. Please download the latest datasheet of PKB24SPCH3601-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=PKB24SPCH3601-B0

## PKB24SPCH3601-B0










### **Applications**

Unsuitable	Please be sure to read and comply with
Applications	these "Precautions for use."
	Consumer equipment,Industrial
	Equipment
	Please refer to Our Website and
	specifications, etc. for information about
Specific	the performance, functions, quality,
Applications	management, and safety required for
	the above applications, and use
	Products after confirming the
	performance and reliability of the actual
	Product.



# Appearance & Shape







### Packaging Information

	Packaging	Specifications	Standard Packing Quantity
	-B0	Bulk	650



### **Features**

This is a unified piezoelectric sounder which has a piezoelectric diaphragm of 3 terminals connected to a self drive circuit, and it easily generates sound with only a DC power supply (DC3.0-20V). Using suitably designed resonant system, this type can be used where large sound volumes are needed.

1 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

Tol.: ±0.5

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Product Search Data Sheet

Note: This datasheet may be out of date.  ${\it Please download the latest datasheet of PKB24SPCH3601-B0 from the official website of Murata}$ Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=PKB24SPCH3601-B0



## **Specifications**

PKB24SPCH3601-B0

Oscillation circuits	D. W.
Oscillation circuits	Built-in
Size	φ24.3×10.0 mm
Frequency	3.6kHz
Sound Pressure Level	90dB (min.)
Measure Condition of Sound Pressure Level	[12Vdc,10cm]
Oscillating Frequency	3.6kHz
Oscillating Frequency Tolerance	±0.5kHz
Measure Condition of Oscillation Frequency	[12Vdc]
Current Consumption(max.)	16mA
Measure Condition of Current Consumption	[12Vdc]
Operating Voltage Range	3Vdc to 15Vdc
Operating Temperature Range	-20°C to 70°C
Storage Temperature Range	-30°C to 80°C
Shape	Lead
Lead Shape	Lead Wire type(Twist type)
Lead length	Lead length:4.5mm
Drive Type	Self Drive
EIAJ Part Number	PB-RPD-C24-36
Mass	3593mg

2 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



### Product Search Data Sheet

Note: This datasheet may be out of date.


Please download the latest datasheet of PKB24SPCH3601-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=PKB24SPCH3601-B0

## PKB24SPCH3601-B0



### **Product Data**



**Voltage Characteristics** 

3 of 3

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

