





PRODUCT DATASHEET

UK to USA Voltage Changer Transformer



-  A 150VA Auto Transformer designed to supply 110V AC from the 240V AC mains.
-  Output is via an American style 2 pin socket and the Input is via a 2 meter mains cable fitted with a BS1363 UK Plug.
-  Encapsulated Construction.
-  Auto-resetting Thermal Trip within Windings.

Note: This unit does not provide mains isolation as the output shares a common neutral with the mains Input. The output frequency is also unchanged.

Weight	1.6	Kg
Typical Regulation	5.5	%
Frequency	50	Hz
Materials	UL94-HB Class "B" 130° C	

Part No	Input	Output
D2734	240V	110V

Please see sheet 2 for dimensions, pin outs and connection information.

DAGNALL ELECTRONICS LIMITED

Shuttleworth Road, Elms Industrial Estate, Bedford. MK41 0EP UK

TEL +44(0)1234 330077 FAX +44(0)1234 330088

E-mail sales@dagnall-electronics.com

Issue 1. 10/07/03

2 of 2

PRODUCT DATASHEET

UK to USA Voltage Changer Transformer

