

Propower Flux Remover

pro-POWER



Description:

A Blend of Solvents designed to remove flux residues from PCB's.

Applications:

- Removal of flux residues from PCB's and components
- Evaporates quickly leaving no residue
- Fast and effective in use
- Also removes uncured surface mount adhesive

Directions:

Spray from a distance of 25 – 30cm liberally onto the area to be cleaned, allow to run off and leave to dry. For heavy deposits further re-application may be required

A Blend of Solvents designed to remove flux residues from PCB's

Note:

May affect some plastics. If unsure test a small area before general use.

Not for use on live electrical equipment. Allow solvent to evaporate completely before turning on power supply

Storage: This product may be stored at normal temperatures and has a shelf life of not less than 36 months with correct storage. Aerosols should always be stored below 50°C, away from direct heat and naked flames

Specifications:

Cleaner Applications	: Computers, Electronics
Dispensing Method	: Can
Colour	: Transparent
Dielectric Strength	: 80V/m
Storage Temperature Max	: 50°C

Technical Data

Appearance	Clear, colourless liquid
Odour	Sweet, solvent
SG at 25°C	0.66
Discharge rate	1.1g/second
Flammability	Classified as extremely flammable under current EC regulations
Flashpoint	Not applicable in sealed aerosol
Pack size	400ml

Part Number Table

Description	Part Number
Pro power Flux Remover 400ml Aerosol	PPC120

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. pro-POWER is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com
www.farnell.com
www.newark.com
www.cpc.co.uk

pro-POWER