

Digital Multimeter



Description

This is a stable, safe and reliable 3-3/4 digit digital multimeter. Whole circuit design to LSI double integral A/D converter as its core, the full range of overload protection circuit, unique design makes it the superior performance of electrical instruments. The instrument can be used to measure AC and DC voltage, DC current, resistance, diodes, circuit continuity, capacitance, frequency / duty cycle or temperature.



Features

- Fused 10A Range : Ceramic fuse
- Relative Mode
- Full Icon Display
- Diode Test
- Continuity Buzzer
- Low Battery Display
- Data Hold
- Auto Ranging
- Input Impedance for DC Voltage Measurement : 10M Ω
- Auto/Manual Range
- Display Backlight
- Max Display : 3,999
- Auto Power Off

Specifications

	Range	Accuracy
DC Voltage (V)	400mV/4V/40V/400V/1000V	$\pm(0.8\%+1)$
AC Voltage (V)	4V/40V/400V/750V	$\pm(1\%+5)$
Communication Bandwidth	40Hz to 400Hz	\surd
DC Current (A)	400 μ A/4000 μ A/40mA/400mA/4A/10A	$\pm(1\%+2)$
AC Current (A)	400 μ A/4000 μ A/40mA/400mA/4A/10A	$\pm(1.5\%+5)$
Resistance (Ω)	400 Ω /4k Ω /40k Ω /400k Ω /4M Ω /40M Ω	$\pm(1\%+2)$
Capacitance (F)	40nF/400nF/4 μ F/40 μ F/100 μ F	$\pm(3\%+5)$
Frequency (Hz)	10Hz to 10MHz	$\pm(0.1\%+3)$
Duty Cycle	0.1% to 99.9%	\surd
Temperature ($^{\circ}$ C)	-40 $^{\circ}$ C to 1000 $^{\circ}$ C	$\pm(1\%+3)$

General Characteristic

Power	9V Battery (6F22)
LCD Size	63mm \times 31mm
Product Colour	Orange and Grey
Product Net Weight	340g
Product Size	177mm \times 85mm \times 40mm
Standard Accessories	Test Lead, Battery, Test Clip, RS232C Interface Cable, PC Software CD
Optional Accessories	Clip-On Test Lead Light, Built-In Test Lead Light, Built-In Test Lead Light Plus
Safety Rating	CAT III 1000V
	CAT IV600V

Part Number Table

Description	Part Number
Hand Held Digital Multimeter	72-7740

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

