

# Palm Size Digital Multimeter **TENMA™**

RoHS  
Compliant



## Features

- 8 Functions
- 2000 Counts Display
- Manual Function Select
- Diode & Transistor Test
- Continuity Buzzer
- Data Hold
- Low Battery Indication
- Input Impedance for DC Voltage: 10M

[www.element14.com](http://www.element14.com)  
[www.farnell.com](http://www.farnell.com)  
[www.newark.com](http://www.newark.com)  
[www.cpc.co.uk](http://www.cpc.co.uk)

**TENMA™**

# Palm Size Digital Multimeter

## General Characteristics

Safety Rating	: CAT III 250V
Power	: 9V Battery (6F22)
LCD Size	: 49mm × 18mm
Colour	: Orange and Grey
Weight	: 200g
Dimension	: 72mm × 137mm × 35mm
Standard Accessories	: Battery, Test Lead, Multi-Purpose Socket, Point Contact Temperature Probe & User Manual

## Electrical Specifications

Parameters	Range	Best Accuracy
DC Voltage	200mV / 2000mV / 20V / 200V / 600V	± (0.5% +2 digit)
AC Voltage	200V / 600V	± (1.2% +3 digit)
DC Current	2000µA / 20mA / 200mA / 10A	± (1% +2 digit)
Resistance	200Ω / 2000Ω / 20kΩ / 200kΩ / 2000kΩ / 20MΩ	± (0.8% +5 digit)
Temperature	-40°C to 1000°C	± (1.0% +3 digit)

## Part Number Table

Description	Part Number
Palm Size Digital Multimeter	72-10390

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.