

ESD Safe Soldering Station



Features

- HD LCD backlight display
- Silver alloy conductive material
- Multi-power switching mode control
- Auto sleep and password locking
- Fault display warning function
- Includes soldering iron, stand, sponge and power cord.

Technical Specifications

Power Consumption	: 90W
Input Voltage	: 220V AC \pm 10% 50Hz
Heater Voltage	: 24V AC
Temperature Range	: 100°C to 500°C (212°F to 932°F)
Temperature Calibration Range	: -50°C to +50°C (-58°F to +122°F)
Password Range	: 001 to 999 (000 means unlocked)
Sleep Temperature	: 200°C
Sleep Time	: 0 to 99 mins
Temperature Accuracy	: \pm 10°C
Temperature Stability	: \pm 2°C (still air)
Tip to Ground Impedance	: \leq 2 Ω
Tip to Ground Voltage	: \leq 2mV
Dimension (L x W x H)	: 168mm x 110mm x 95mm
Weight	: 2kg

Part Number Table

Description	Part Number
Soldering Station, ESD Safe, 90W, 220V AC, 500°C Max. Temp., UK plug	AT-90DH-UK
Soldering Station, ESD Safe, 90W, 220V AC, 500°C Max. Temp., EU plug	AT-90DH-EU

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com
www.farnell.com
www.newark.com
www.cpc.co.uk



Dual Function Bench Fan and Solder Smoke Absorber



Product Overview

- Dual function: It can be used as a bench fan or as a solder smoke absorber.
- The fan is designed to sit on a desktop or can be hung from a support beam.
- 1 carbon fibre filter is included.
- Low noise and long life service fan.


Specifications

Power : 23W
Absorption Capacity : 0.2-1M³/minute (Max)
Airflow volume : 0.2-1.2M³/minute (Max)

Operation

- Position the fan as required.
- If using the bench fan function, face the front side towards you.
- If using the smoke absorber function, make sure the carbon filter has been inserted, and face the reverse side towards the solder smoke.
- Plug the fan into a mains power outlet.
- Activate the on/off Switch.
- To change the fan speed from 1 to 10, adjust the speed control

Diagram



Part Number Table

Description	Part Number
Dual Function Bench Fan and Solder Smoke Absorber	D03288

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. DURATOOL is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com
www.farnell.com
www.newark.com
www.cpc.co.uk

