



XTR-ZB1-xLI

Pin-Out

1) Vcc

2) GND

4) ADC1

5) RSTX

6) RSRX

7) RTS 8) CTS

9) ADC3

10) GND

11) ADC2

12) ADC4

3) INPUT R.

- High efficiency (XTR-ZB1-RLI) and high power (XTR-ZB1-RHI) modules for best coverage of wide areas.
- PC operative interface through OCX file which can be easily embedded into the customer high level language program (Visual Basic, Visual C, Java, etc, allowing the convenient network handling.
- Application software in Visual Basic language for usage of Aurel OCX component which shows how to create, manage and monitor the network by means of high level commands without needing any further pieces of information regarding the network itself.
- Possibility of automatic RF channel switch in case of external interferences and automatic rebuilding of whole network within 3 minutes.
- Mesh-type data transmission among network nodes by utilizing only ASCII strings made up of address+data format.
- Possibility to lock the network once it is built up and working, allowing the highest control even in presence of other nearby Zigbee networks.
- Automatic and user transparent encrypted data transmission (128 encryption
- Commands set by ASCII strings for low level module usage.

13) OUT 1

14) OUT R.

15) OUT 3

16) OUT 2

18) OUT 4 19) IN 3

17) IN 1

20) IN 2

22) PWD

23) GND

24) RESET

35 mm PIN 1 21) INTERRUPT CONNECTOR SOLDERING SIDE

XTR-ZB1-xLI XTR-ZB1router R coordinator C end device RF high power H RF low power L integrated antenna external antenna

Application

Start up of Zigbee network with high level software support for best network management and control.

XTR-ZB1-RLI, XTR-ZB1-CLI, XTR-ZB1-ELI

Ta = 25 °C

Characteristics	Min	Тур	Max	Unit
Voltage supply	2.0	3.3	3.6	Vdc
Current supply (RX mode)		33		mA
Current supply (TX mode)		28		mA
Current supply (power down)			1	μΑ
Modulation type		O-QPSK		
Receiver sensitivity		-92		dBm
RF Power out (ERP)		0		dBm
RF channels frequencies	2405		2483	MHz
Number of channels		16		
RF bandwidth		2		MHz
RF data rate (raw)		250		kbps