



LICENSE-FREE WALKIE TALKIES

Handfunkgerät

Transceptor

Talkie Walkie

MT100

16* Channels

* Only Channels 1 to 8 are available by default. Channels 9 to 16 need to be activated by user before they can be selected.)

Up to 3 km Range

Compact design with extended range.

Roger Beep

Confirmation tone indicates to others it's clear to talk.

Power Saver Circuitry

Unique circuit extends battery life when not transmitting or receiving.

Call Alert

Provides a recognizable alert for incoming calls.



Nothing Comes Close to a Cobra®

www.cobrapmr.com

Features

Benefits

UHF/FM	Ultra-clear long distance reception.
Up to 3 km Range	Extended range capability provides up to 3 km range. (Range will vary depending on terrain and conditions.)
16* Channels	Easy access to 16* channels. Works with other PMR walkie-talkie 2-way radios.
121 Privacy Codes	38 CTCSS (Continuous Tone Coded Squelch System) codes and 83 DCS (Digitally Coded Squelch) codes provide a total of 121 privacy codes. 1936 privacy combinations are possible when the 16 channels are combined with the 121 privacy codes.
Battery Saver Circuitry	A unique circuit extends the life of the batteries. If there are no transmissions within 10 seconds, the unit will automatically switch to battery saver mode.
Scan Feature	Allows the user to scan either channels or privacy codes within a channel to locate conversations in progress.
Call Alert	Provides an easily recognizable alert for incoming calls.
Roger Beep Tone	Confirmation tone indicates the completion of the user's transmission, and signals to others it is clear to talk.
Auto Squelch	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.
LCD Display	Easy to view display provides the radio's status at a glance.
Keystroke Tone Signal	Confirms key activation.
Belt Clip	Secures your microTALK® radio while on the go.
No Licence or Service Fess	High quality band frequencies with no fees.

* Only Channels 1 to 8 are available by default. Channels 9 to 16 need to be activated by user before they can be selected. Channels 9 to 16 should only be used in countries where these frequencies are allowed by government authorities.

Unit Specifications - General

Unit Dimension	131mm x 49mm x 36mm (5.16" x 1.93" x 1.42")		SKU#	MT100
Unit Weight	70g (2.47oz)		UPC	810026630880
16* Channels	Channel	Freq.(MHz)	Gift Box Dimension	142mm x 86mm x 86mm (5.59" x 3.39" x 3.39")
	1	446.00625	Gift Box Weight	195g (6.88oz)
	2	446.01875	Master Pack Qty	4
	3	446.03125	Master Pack Bar Code	10810026630887
	4	446.04375	Master Pack Dimension	160mm x 184mm x 184mm (6.30" x 3.31" x 3.31")
	5	446.05625	Master Pack Weight	920g (32.45oz)
	6	446.06875	Battery Pack	3 AAA alkaline batteries per radio (not included)
	7	446.08125		
	8	446.09375		
	9	446.10625		
	10	446.11875		
	11	446.13125		
	12	446.14375		
	13	446.15625		
	14	446.16875		
	15	446.18125		
	16	446.19375		

8 Language Manual Includes:



English



Spanish



Swedish



French



Romanian



Dutch



German



Portuguese

<Specifications subject to change without notice>
<All dimensions (H x W x D)>

Cobra®, microTALK®, Nothing Comes Close to a Cobra®, and the snake design are registered trademarks of Cobra Electronics Corporation, USA.

Cobra Electronics Corporation™ is a trademark of Cobra Electronics Corporation, USA.

©2021 Altis Technology (Hong Kong) Ltd



* Packaging is made from recyclable materials.

Nothing Comes Close to a Cobra®