

**RoHS
Compliant**



Description

This VGA+R/L to HDMI Scaler Converter converts VGA input into HDMI and allows computer users to enjoy their larger image on TV. The Converter is also along with the R/L audio to allow you to enjoy high quality sound on the HDTV. With built-in scaler function, no matter what resolution computer's VGA port set, this converter will fix to output HDMI 1920X1080 resolution with the best compatibility.

Features

- Easy to Use: Install in seconds, no need of setting.
- Convert computer's VGA video and R/L audio into HDMI signal.
- Supports all kinds of common resolution of computer's VGA port.
- Supports HDMI resolution to fixed 1280×720P and 1920×1080P
- Supports HDMI 165MHz/1.65Gbps per channel (6.75Gbps all channel) bandwidth.
- Supports HDMI 8bit per channel (24bit all channel) deep colour.

Specifications

Signal Inputs/Output	
Input Signal	VGA, R/L
Output Video signal	HDMI 720P/1080P
VGA Resolution	640x480 60/72/75/85Hz 800x600 60/72/75/85Hz 1024x768 60/70/75/85Hz 1280x720 60Hz 1280x768 60/75/85Hz 1280x800 60/70/75Hz 1280x960 60Hz 1280x1024 60Hz 1440x900 60Hz 1920x1080 60Hzs 1920x1200 60Hz 1920x1440 60Hz Note: Maybe several resolutions are limited on few displays
Operating Frequency	
Vertical Frequency Range	50/60Hz
Video Amplifier Bandwidth	1.65Gpbs/165MHz
Mechanical	
Size (W×H×D)	88mm×25.5mm×68mm

Weight (Net)	0.68kgs
Environmental	
Operating Temperature	0°C to +45°C
Operating Humidity	10% to 85% RH (no condensation)
Storage Temperature	-10°C to +80°C
Storage Humidity	5% to 95% RH (no condensation)
Power Requirement	
External Power Supply	5V DC @ 2A
Power consumption (Max)	4 watts
Warranty	
Limited Warranty	12 Months
Regulatory Approvals	
Converter Unit	FCC, CE
Power Supply	CE, FCC
Accessories Adapter	
AC Power Adapter	US standard, UK standard and so on
User Manual	

Connection and Operation

- 1) Connect the VGA video and R/L audio from computer to this product. (Input cables are optional)
- 2) Connect the HDMI output from this product to the TV which has HDMI input.
- 3) Connect the VGA and R/L audio output of this product to the computer's monitor and speaker if necessary.
- 4) Insert the DC side of 5v power supply into this product and then connect the AC side of the power supply into the wall outlet.
- 5) Power on the computer and TV, choose the input of TV to its HDMI channel.
- 6) Press the button to switch 720P or 1080P

Part Number Table

Description	Part Number
VGA+R/L to HDMI Scaler Converter	PSG03649

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. pro-SIGNAL is the registered trademark of Premier Farnell Limited 2019.