



IDEAL NETWORKS

NavITEK NT Plus & Pro

Upgrade Instruction



NaviTEK NT Plus & Pro Software Release Notes

Summary:

Release v1.0.68 replaces the previous production release (v1.0.49) and all previous versions of NaviTEK NT Plus & Pro including v1.0.40.

Main changes:

- Added Japanese language support.
- Added TP Link wireless dongle (TL-WN725N Ver:3.0) support of IDEAL AnyWARE
- Added built-in LLDP/CDP/EDP packets capture function for debugging
- Support Edimax EW-7811Un V2 new version USB-Wi-Fi dongle

NaviTEK NT Plus & Pro Software Update Procedure

To update units with serial numbers starting with 151 (NaviTEK NT Plus & Pro) to the current software version (v1.0.68 onwards):

CATION:

- This upgrade is none reversible back to previous version
- All saved data will be erased after upgrading. Please make sure all your data is backed up before upgrading.

1. Copy the file NaviTEK-NT-md5.bin to a USB memory key
2. Ensure that the tester is connected to the mains power supply or that the battery is fully charged
3. Switch the tester ON
4. Insert the USB memory key into the tester
5. Save any results stored in the tester (all data and settings will be lost following the software update) to USB memory key
6. From the HOME screen, select F3 (MORE) / F1 (SETUP) / SYSTEM / UPDATE
7. Select F1 (UPDATE)
8. Wait for the update to be completed
9. **Manual factory default RESET:** from home page, select any test mode icon (Auto, Cable, Switch, Network)/MORE (F3) / SETUP (F1) /SYSTEM / FACTORY / RESET(F1),
10. To check current installed version, from HOME screen, select any test mode icon (Auto, Cable, Switch, Network) / MORE (F3) / SETUP (F1) /SYSTEM / ABOUT

WARNING: You MUST conduct manual FACTORY default RESET after the software upgrades otherwise the tester's functions may NOT perform properly.



IDEAL NETWORKS

IDEAL INDUSTRIES Networks Limited
Stokenchurch House, Oxford Road, Stokenchurch,
High Wycombe, Bucks, HP14 3SX, UK.

www.idealnetworks.net