



IDEAL NETWORKS

# NaviTEK IE

## Upgrade Instruction



## **NaviTEK IE Software Release Notes**

### **Summary:**

Release v1.0.68 is the production release to replace v1.0.63 and all previous software versions.

### **Known main fixes:**

This SW v1.0.68 has following new and fixes vs v1.0.63 release:

- Added Japanese language support.
- Added TP Link wireless dongle (TL-WN725N Ver:3.0) support for IDEAL AnyWARE
- Added built-in LLDP, SNMP packets capture and replay function to avoid external PC and hub required for debugging Discovery port info and SNMP/PROFINET request & response messages.
- Blanks Pages in PDF Report when SNMP requests failed to receive response

### **Known main issues:**

Things are not available/issues in this version:

- The IDEAL AnyWARE CSV transfer via Android is limited to 4Kbytes.

# NaviTEK IE Software Update Procedure

To update units with serial numbers starting with 151 (NaviTEK IE or converted from NT to IE) to the current software version (v1.0.58 onwards):

## CATION:

- This software is only valid for the booting up screen showing NaviTEK IE. Any booting UP screen showing NaviTEK NT will not applicable).
- This upgrade is none reversible back to previous version
- All saved data will be erased after upgrading. Please make sure all your data is backed up before upgrading.
- A correct upgrade file NaviTEK-NT-md5.bin or NaviTEK -IE-md5.bin needs to be selected based on current installed version.

1. Ensure that the tester is connected to the mains power supply or that the battery is fully charged
2. Switch the tester ON
3. Check the current software version installed in NaviTEK (Home - SETUP/System/About)
4. If the installed current software version is [v1.0.55 or higher](#), copy the latest file NaviTEK-IE-md5.bin from your PC to the root directory of USB memory key
5. Insert the USB memory key into the tester
6. Save any results stored in the tester (all data and settings will be lost following the software update) to USB memory key
7. From the HOME screen, select F3 (MORE) / F1 (SETUP) / SYSTEM / UPDATE, then Select F1 (UPDATE)
8. Wait for the update to be completed
9. **Manual factory default RESET:** from home page, select SETUP (F3) /SYSTEM / FACTORY / RESET(F1),
10. To check current installed version, repeat step 3.

## WARNING:

- You MUST copy ONLY ONE .bin file in the root directory of USB memory key. Otherwise, your upgrade will be failed.
- You MUST conduct manual FACTORY default RESET after the software upgrades otherwise the tester's functions may NOT perform properly.



**IDEAL NETWORKS**

IDEAL INDUSTRIES Networks Limited  
Stokenchurch House, Oxford Road, Stokenchurch,  
High Wycombe, Bucks, HP14 3SX, UK.

[www.idealnetworks.net](http://www.idealnetworks.net)