
KEMET Part Number: T495X476K035ATE185



Capacitor, Tantalum, SMD, MnO2, Molded, Low ESR, 47 uF, 7343, +/-10% Tol, 35 VDC (85C)



| General information | | |
|------------------------|----------------------------|--|
| Supplier: | KEMET | |
| Application: | Low ESR | |
| Part Type Description: | SMD, MnO2, Molded, Low ESR | |
| Construction: | Standard Chip-MnO2 | |
| Body Type: | SMD Chip | |
| Footprint: | 7343 | |
| Weight: | 652.04 mg | |
| RoHS: | Yes | |
| | | |

General Information

| Dimensions (mm) | | |
|-----------------|-----------|-----------|
| Symbol | Dimension | Tolerance |
| L | 7.3 | +/-0.3 |
| W | 4.3 | +/-0.3 |
| Н | 4 | +/-0.3 |
| F | 2.4 | +/-0.1 |
| S | 1.3 | +/-0.3 |
| В | 0.5 | +/-0.15 |
| Х | 0.1 | +/-0.1 |
| Р | 1.7 | REF |
| R | 1 | REF |
| Т | 0.13 | REF |
| A | 3.6 | MIN |
| G | 3.5 | REF |
| E | 3.5 | REF |

| Specifications | | |
|-------------------------|--------------------|--|
| Capacitance: | 47 uF | |
| Tolerance: | +/-10% | |
| Voltage: | 35 VDC (85C) | |
| Voltage: | 23.45 VDC (125C) | |
| Temperature Range: | -55/+125C | |
| Current/Ripple Current: | 944 mAmps (25C) | |
| Current/Ripple Current: | 849.6 mAmps (85C) | |
| Current/Ripple Current: | 377.6 mAmps (125C) | |
| Resistance/ESR: | 185 mOhms (100kHz) | |
| Failure Rate: | N/A | |
| Leakage Current: | 16.5 uA | |
| Dissipation Factor: | 8% | |

| Packaging Specifications | | |
|--------------------------|-------------|--|
| Package Kind: | T&R | |
| Package Size: | 7 in/180 mm | |
| Package Quantity: | 500 | |

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.

