



# 45V, 3A Half-Bridge Power Driver Evaluation Board, AEC-Q100 Qualified

#### **DESCRIPTION**

The EVQ6610-J-00A is an evaluation board for the MPQ6610GJ, a half-bridge power driver.

The EVQ6610-J-00A operates from a supply voltage of up to 45V, and can deliver load currents up to 3A. The input control signals for the MPQ6610 are either generated on the board, or from an external controller through the board's connector (P1).

The MPQ6610GJ is available in a TSOT23-8 package.

#### **ELECTRICAL SPECIFICATIONS**

Parameter	Symbol	Value	Units
Input voltage	$V_{IN}$	4 to 45	V
Maximum output current	louт-l	3	Α

#### **FEATURES**

- Wide 4V to 45V Input Voltage Range
- Up to 3A Output Current
- Internal Current Sense
- 2.5V, 3.3V, or 5V Compatible Logic Supply
- Over-Current Protection (OCP), Over-Voltage Protection (OVP), Over-Temperature Protection (OTP)
- Fault Indication Output
- Available in a TSOT23-8 Package
- AEC-Q100 Qualified

#### **APPLICATIONS**

- Solenoid Drivers
- Brushed DC Motors
- Relay Drivers

All MPS parts are lead-free, halogen-free, and adhere to the RoHS directive. For MPS green status, please visit the MPS website under Quality Assurance. "MPS", the MPS logo, and "Simple, Easy Solutions" are trademarks of Monolithic Power Systems, Inc. or its subsidiaries.

## **EVQ6610-J-00A EVALUATION BOARD**



LxW (6.35cmx6.35cm)

Board Number	MPS IC Number	
EVQ6610-J-00A	MPQ6610GJ	



#### **QUICK START GUIDE**

- 1. Attach the input voltage ( $4V \le V_{IN} \le 45V$ ) to the VIN connector, and attach the input ground to the GND connector.
- 2. Attach the VCC voltage (2.5V, 3.3V, or 5V) to the VCC connector, and attach the input ground to the GND connector.
- 3. Input control signals can be generated on the board through the placement of short jumpers (JP1 and JP2), or by an external controller connected through the P1 connector. If using an external controller, remove the short jumpers (JP1 and JP2). Table 1 shows the input logic truth table.


**Table 1: Logic Truth Table** 

EN	IN	OUT
0	0	Z
0	1	Z
1	0	L
1	1	Н

4. The output current limit threshold is reached when the ISET pin reaches 1.5V. The ISET pin voltage scaling is set by the trimming potentiometer (RV1). For example, if a 10kΩ resistor is connected from ISET to ground, the ISET pin voltage is 1V for every 1A of output current. This means that when the current reaches 1.5A, the ISET pin voltage reaches 1.5V, and a current trip occurs.



## **EVALUATION BOARD SCHEMATIC**



**Figure 1: Evaluation Board Schematic** 



# **EVQ6610-J-00A BILL OF MATERIALS**

Qty	Ref	Value	Description	Package	Manufacturer	Manufacturer P/N
1	C1	100µF	100V, electrolytic capacitor	DIP	Jianghai	CD263-100V100
1	C2	2.2µF	100V, ceramic capacitor, X7R	1210	Murata	GRM32ER72A225KA35L
1	C3	100nF	100V, ceramic capacitor, X7R	0603	Murata	GRM188R72A104KA35D
2	C4, C5	100nF	25V, ceramic capacitor, X7R	0603	Murata	GRM188R71E104KA01D
3	R1, R2, R3	1kΩ	Film resistor, 1%	0603	Yageo	RC0603FR-071KL
1	R4	4.99kΩ	Film resistor, 1%	0603	Yageo	RC0603FR-074K99L
1	RV1	10kΩ	Square trimming potentiometer	DIP	Bourns	3266W-1-103F
1	LED1	Red	LED	0805	Baihong	BL-HUE35A-AV-TRB
1	D1	NS				
3	JP1, JP2, P1	2 bits/ 2.54mm	Connector	DIP	Any	
2	JP1, JP2	2.54mm	Short jumper	DIP	Any	
2	FLT, VSET	Yellow	Test point	DIP	Any	
4	VIN, VIN_GND, OUT, LOAD_GND	Φ = 2mm	Connector, 2mm needle	DIP	Any	
3	VCC, VCC_GND, GND	Φ = 1mm	Connector, 1mm needle	DIP	Any	
1	U1	45V, 3A	Half-bridge power driver	TSOT23-8	MPS	MPQ6610GJ

4



# **PCB LAYOUT**




Figure 2: Top Silk Layer

Figure 3: Top Layer

5




Figure 4: Bottom Layer



### **REVISION HISTORY**

Revision #	Revision Date	Description	Pages Updated
1.0	3/11/2021	Initial Release	-

**Notice:** The information in this document is subject to change without notice. Please contact MPS for current specifications. Users should warrant and guarantee that third-party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.