© GLENAIR UK LTD - 12/12/2013

KIT COMPRISES:
MICRO-D BACKSHELL
SINGLE LAYER TIN COPPER BRAID
HEATSHRINK BOOT
MALE JACKSCREW HARDWARE
BAND STRAP



TABLE 2 CABLE ENTRY		
CABLE ENTRY	SHELL SIZE	'E' ENTRY DIA
04	09 TO 100	3.2
05	09 TO 100	4.0
06	09 TO 100	4.8
07	09 TO 100	5.6
08	09 TO 100	6.4
09	31 TO 100	7.1
10	51 TO 100	7.9
11	100 ONLY	8.7
12	100 ONLY	9.5



PART NUMBER DEVELOPMENT

508T152M15H08-4T

BASIC PART NUMBER
MATERIAL/FINISH CODE
SHELL SIZE (TABLE 1)
HARDWARE
CABLE ENTRY (TABLE 2)
BRAID LENGTH (INCHES)
BOOT OPTION (SEE GLENAIR 77 SERIES FOR INFORMATION)

TABLE 1 DIMENSIONS				
SHELL SIZEE	'A'	'B'	'C'	'D'
09	19.7	9.1	14.4	8.1
15	23.5	9.1	18.2	11.2
21	27.3	9.1	22.0	14.2
25	29.8	9.1	24.5	15.7
31	33.7	9.1	28.3	17.3
37	37.5	9.1	32.1	18.3
51	36.2	10.2	30.9	19.1
100	54.9	11.4	45.7	20.6



REV.	DCO No.	DATE
B	10643	11/12/13

TITLE

MICRO-D EMI/RFI LOW HEIGHT BANDING ADAPTOR AND HEATSHRINK BOOT KIT

EPF	DIS	DRAWN BY	DATE	SHT 1 OF 1
	9100	A.Charlton	28-11-2013	

DESIGN APPROVAL	DATE	DRAWING NUMBER
S.Carter	12/12/2013	508-152

GLENAIR UK LTD
OAKHAM BUSINESS PARK
MANSFIELD, NOTTINGHAMSHIRE
UNITED KINGDOM.

REVISION
ALL DOCUMENTS UNDER THIS DRAWING NUMBER ARE AT REVISION B