|                                  | PART NO.<br>ABT-402-RC |  |                 | REVISIONS   |       |          |        |          |         |          |
|----------------------------------|------------------------|--|-----------------|---|-------|----------|--------|----------|---------|----------|
| Pro-SIGNAL                       |                        |  | REV             | DESCRIPTION   | DRAWN | DATE     | CHECKD | DATE     | APPRVD  | DATE     |
|                                  |                        |  | А               | RELEASED  |       | 06/04/09 | Veena  | 06/04/09 | Farnell | 20/04/09 |
|                                  |                        |  |                 |   |       |          |        |          |         |          |
| Potting $6.8$<br>Tolerance: ±0.5 |                        |  | PCB m<br>Sealed | es:<br>ower consumption.<br>nountable.<br>I base.<br>solderable and washable. |       |          |        |          |         |          |

Dimensions : Millimetres

## All data at 25°C unless otherwise specified.

| Specifications                                   | ABT-402-RC Piezo Transducer |  |  |  |  |
|--|-----------------------------|--|--|--|--|
| Rated Voltage (Vp-p Square Wave)                 | 5Vp-p                       |  |  |  |  |
| Operating Voltage                                | 1 to 20Vp-p                 |  |  |  |  |
| Rated Current at Rated Voltage                   | 1mA                         |  |  |  |  |
| Capacitance                                      | 13,000 ±30%pF               |  |  |  |  |
| Sound Output at 4000Hz at 10cm, at Rated Voltage | ≥80dB                       |  |  |  |  |
| Resonant Frequency                               | 4000 ±500Hz                 |  |  |  |  |
| Operating Temperature                            | -20 to +70°C                |  |  |  |  |
| Storage Temperature                              | -30 to +80°C                |  |  |  |  |
| Weight   | 1g                          |  |  |  |  |

## Part Number Table

|  |  | Description<br>Piezo Transducer, 5V, PCB   | Part Number<br>ABT-402-RC |   |              |              |            |             |                                  |        | vww.newark.com<br>vww.cpc.co.uk |  |
|--|--|--|---------------------------|---|--------------|--------------|------------|-------------|----------------------------------|--------|---------------------------------|--|
|  | This data sheet and its contents (the "Information") belong to the Premier Farnell Group<br>(the "Group") or are licensed to it. No licence is granted for the use of it other than for<br>information purposes in connection with the products to which it relates. No licence<br>of any intellectual property rights is granted. The Information is subject to change with-<br>out potice and replaces all data sheet provides the products the provides the transmission of the transmissio |  | CES:                      | DRAWN BY:   | DATE:        | DRAW         | ING TITLE: |             |                                  |        |                                 |  |
|  |  |  | THERWISE                  | Venkat  | 06/04/09     | ] ABT-402-R0 |            |             | <ul> <li>Piezo Buzzer</li> </ul> |        |                                 |  |
| out notice and replaces all data sheets previously supplied. The Information supplied is<br>believed to be accurate but the Group assumes no responsibility for its accuracy or<br>completeness, any error in or omission from it or for any use made of it. Users of this |  | CHECKED BY:  | DATE:                     | SIZE DWG NO.                                      |              |              | FLEC       | TRONIC FILE |                                  |        |                                 |  |
| c<br>L   | data sheet should check for themselves the Information and the suitability of the prod-<br>ucts for their purpose and not make any assumptions based on information included or<br>omitted. Liability for loss or damage resulting from any reliance on the Information or   |  |                           | DIMENSIONS ARE<br>FOR REFERENCE<br>PURPOSES ONLY. | Veena        | 06/04/09     | Δ          | Biro no.    |                                  |        | 97 DWG                          |  |
| . L  |  |  |                           |   | APPROVED BY: | DATE:        | -          |             |                                  | 100077 |                                 |  |
| or restrict  |  | the Group's liability for death or personal injury resulting from its n<br>IGNAL is the registered trademark of the Group. © Premier Farne | egligence.                |   | Farnell      | 20/04/09     | SCAL       | .E: NTS     | U.O.M.: mm                       |        | SHEET: 1                        |  |

http://www.farnell.com

REV

А

SHEET: 1 OF 1