

American Electronic Components, Inc.

1101 Lafayette Street, Elkhart, IN 46516, Tel: (574) 295-6330, Fax: (574) 293-8013, sales @aecsensors.com

DURAKOOL Series CBC (Closed) 100 Amps

Durakool mercury contactors are a favorite choice for high reliability lighting and heating control. Their low maintenance and excellent tungsten in-rush handling characteristics provide dependable long-term operation. CFC (normally open) and CBC (normally closed) contactors are general purpose rated at 100 Amps. Top and bottom compression-lug connectors provide secure connection.

"C" size Durakool contactors have mercury-to-tungsten contacts for easy handling of inductive, tungsten, motor and resistive loads. Tungsten's resistance to arcing erosion prolongs the life of the contactor.

SPECIFICATIONS

Maximum Time:OperateReleaseNormally Open:90 ms140 msNormally Closed:200 ms100 msContact Bounce, Release:Allowed on normally open models

Recommended

DC Load Polarity: Top Connector Negative
Load Connectors: Pressure Connector #1-8 AWG Cu.

Coil Terminals: #6-32 Wire Binding Screw,

Max. *12 AWG Cu.

Breakdown Voltage: 5000 VRMS/Min. Across Contacts



| TYPE/SERIES | | CBC (Normally Closed) | | | | | | | | |
|-------------|---------|-----------------------|---------|-------|-------|--|--|--|--|--|
| | | Typical Coil Data | | | | | | | | |
| DESCRIPTION | | Part Number | DC Ohms | Watts | Amps | | | | | |
| | Volts | | | | | | | | | |
| 1 Pole | 24 | CBC-701 | 7.1 | 7.7 | 0.837 | | | | | |
| | 120 | CBC-702 | 180 | 8.5 | 0.179 | | | | | |
| | 208 | CBC-703 | 600 | 7.6 | 0.087 | | | | | |
| | 240 | CBC-704 | 680 | 9.3 | 0.093 | | | | | |
| | 277 | CBC-705 | 1000 | 8.0 | 0.070 | | | | | |
| | 480 | CBC-706 | 2700 | 9.4 | 0.046 | | | | | |
| | 12 (DC) | CBC-719 | 27 | 5.3 | 0.441 | | | | | |
| | 24 (DC) | CBC-707 | 1111 | 5.2 | 0.217 | | | | | |

| ELECTRICAL RATINGS | GENERAL PURPOSE 0.7/0.8 UL Power Factor | | DC | | Tungsten Lamp/60 Hz | | AC MOTO | | R LOAD 3 Phase | | | | | |
|--|--|-----------|-----------|-----------|------------------------|-----------|---------|----------|-------------------|-----------|--------------|------------|-----|----------|
| Volts | 120 | 208 | 240 | 277 | 480 | 600 | 1-48 | 120 | 240 | 120 | | 120 | 240 | 240 |
| SERIES | 60 Hz Amps | | | DC Amps | | Amps | KW | Нр | Нр | Нр | | | | |
| CFC 100 (Normally Open) CBC 100 (Normally Closed) | 100 | 100 90 | 100 90 | 100 60 | 100 60 | 100 70 | 100 | 50 50 | 30 30 | 100 90 | 12.0 10.8 | 7.5 7.5 | 10 | 20 20 |



American Electronic Components, Inc.

1101 Lafayette Street, Elkhart, IN 46516, Tel: (574) 295-6330, Fax: (574) 293-8013, sales @aecsensors.com

DURAKOOL Series CBC (Closed) 100 Amps



