Customer:

No. SW065104A

Date: 2006 - 07 - 20

ALPS EUROPE DISTRIBUTION

Attention:

Your ref. No.:

Your Part No.: SPUN191000

SPECIFICATION

ALPS';

MODEL: SPUN191000

Spec. No.: SPUN-S-501

Sample No.: F3289997M

REC	EIPT STATUS
REC	EIVED
Ву	Date
	Signature
	Name
	Title



K. DSG'D Tomita

APP'D **K.ITO**ENG. DEPT. DIVISION

Sales

Head Office 1-7,Yukigaya-otsuka-cho,Ota-ku,Tokyo.145-8501 Japan Phone.+81(3)3726-1211

SPUN-S-501 1. General 1.1 Application This specification is applied to low current circuit (Secondary circuit) push switch used for electronic equipment. 1.2 Operating temperature range : -10 ~ 60℃ 1.3 Test conditions The standard test conditions shall be 5~35°C in temperature, 45~85% RH and 86~106kPa (880~1060mber) in atmospheric pressure. Should any doubt arise in judgement, tests shall be conducted at 20±2°C, 65±5% RH and 86~106kPa (860~1080mbar) 2. Appearance, construction and dimensions 2.1 Appearance Switch shall have good finishing, and shall have no rust, crack or plating failures. 2.2 Construction and dimensions Per individual product drawing 2.3 Markings' Per individual product drawing 3. Rating 30 V DC 0.1 A (Resistive load). A Minimum rating / V DC 10 uA Electrical performance Items Test conditions Criterion Contact resistance | Shall be measured at 1kHz ± 200Hz (20mV MAX , 50mA MAX) or 1A, 5V DC 20 mQ HAX by voltage drop method. Insulation Test voltage: 500 V DC, measured after 1 minute ±5 seconds. 100 HΩ HIN resistance Applied position : Between all terminals Between terminals and ground (frame) Test voltage: 500 V AC (50~60Hz, cut-off current 2 mA) 4.3 Voltage proof No dielectric breakdown shall occur. Applied position : Between all terminals Between terminals and ground (frame) 4 4 Shall be measured at 1MHz ± 10kHz Capacitance 1.5 pF MAX Between all terminals Between terminals and ground (frame) Between all circuits 4.5 Changeover timing As per individual product drawing. Mechanical performance Test conditions Items Criterion Operating force A static load shall be applied to the tip of actuator in operating As per individual product drawing. direction. 5.2 Terminal strength 5 N 4-510 xf) Ashall be applied to the tip of Shall be free from terminal looseness terminal in a desired direction for 1 minute. The number of test shall and damage and breakage of terminal be once per terminal. holding portion. Terminals may be bent after test, electrical performance requirement specified in item 4 shall be satisfied. Thread shall be mounted at O.7 N·m +7.14 kaf-cm/ by normal Mounting strength Shall be free from damage of thread of thread portion mounting method. portion. (1) A static load of 50 N + 5 | keff Shall be applied in the Control strength Shall be free from pronounced wobble. 5.4.1 Control operating direction of actuator for 15 seconds. bending and mechanical abnormalities. (2) A static load of 50 N = 5.1 kaf) Shall be applied in the strength pull direction of actuator for 15 seconds. (For construction with lock, the test shall be conducted at the condition of lock released.) (3) A-static load of 30 N 300 Shaff shall be applied to the vertical direction of operation at the tip of actuator for 15 seconds. (1) A static load of 10 N + 102 heft/2 shall be applied in the pull direction at the condition of locking actuator. 5.4.2 Lock hold-Lock shall not be dislocated. ing strength of Shall be free from pronounced wobble actuator and abnormalities in operation. (Applied to the switch with lock mechanism) Run-out(P-P) shall be measured by applying a static load of 1N (102sf) P-P: O.8 mm MAX Wobble of actuator in the vertical direction of operation at the tip of actuator. Without frame: 1.2mm MAX 5.6 Roy of actuator Switch shall be mounted as shown. Difference of sides shall be Difference between actuators (Applied to measured. t₁ = Vithin <u>0.5</u> mm multipul-key Maximum difference of actuator push switch) $t_2 =$ Within 0.8Difference between mounting hole and actuator ts = Within 0.5 mm Hole for mounting frame APPD CHKD. DSGD. TITLE M. Jun,4'93 Teb.19,18 T.W 7.W DRAWING NO.

BACKGROUND ALPS ELECTRIC CO., LTD.

PAGE SYMB DATE APPD CHKD DSGD

		· (Pu
SPUN-S-50	SPUN PRODUCT SPECIFICATIONS	••
Items	Test conditions	Criterion
5.7 Mounting frame strength (Applied to multipul-key push	Both ends of mounting frame shall be secured. A static load of 30 N +3.06 keff shall be applied to the center of mounting frame in A, B, C and D directions each 15 seconds.	Warp on mounting frame shall be 0.51 max. Shall be free from abnormalities in operation.
switch)	A - BEEF B	
9 11:1	Fixed D D	
.8 Vibration	Switch shall be secured to a testing machine by a regular mounting device and method. (1) Vibration frequency range: 10~55Hz (2) Total amplitude: 1.5mm	Contact resistance (Item 4.1): 20 mΩ MAX Insulation resistance (Item 4.2): 100 MΩ MIN
	(3) Sweep ratio: 10-55-10(Hz) Approx. 1 minute (4) Hethod of changing the sweep vibration frequency: Logarithmic or linear (5) Direction of vibration: Three vertical directions	Voltage proof (Item 4.3): Apply 500 V AC for 1 minute. No dielectric breakdown shall occur Operating force (Item 5.1):
9 Mechanical shock	including actuator. (6) Time: 2 hours each (6 hours in total) Switch shall be measured after following test.	Within ±30 % of specified value. No abnormalities shall be recognized in appearance and construction. Contact resistance (Item 4.1):
5.9.1 Mechanical shock	(1) Hounting method: Hormal mounting method (2) Acceleration: 490m/s ² (500) (2) (3) Buration: 11ms (4) Test direction: 6 directions	20 mΩ MAX Operating force (Item 5.1) Within ± 10 % of specified value. Shall be free from mechanical
5.9.2 Lock holding	(5) Number of shock: 3 times per direction (18 times in total) Switch shall be conducted at the condition of locking actuator.	abnormalities. (Dislocation of lock of actuator shal not be regarded as abnormalities.)
shock (Applied to the switch with lock mechanism.)	(1) Acceleration: 147 m/s ² + 15 G + A (2) Duration: 11 ms	Lock of actuator shall not be dis- located. Shall be free from abnormalities in operation.
0 Solderability	(4) Number of shock: 3 times per direction (18 times in total) Switch shall be checked after following test.	4
	(1) Solder: H63A (JIS Z 3282) (2) Flux: Rosin flux (JIS K 5902) having a nominal composition of 25% solids by weight of water white rosin in methyl alcohol (JIS K 1501) solution.	More than 90% of immersed part shall be covered with solder.
	(3) Soldering temperature : 230±5℃ Immersing time : 3±0.5 s Flux immersing time shall be 5~10 seconds in normal temperature. (4) Immersion depth : Immersion depth shall be at copper plating	
	portion for P.C.B. terminal after mounting. Thickness of P.C. board : 1.6 mm	
Soldering heat resistance	(1) Solder: H63A (JIS Z 3282) (2) Flux: Rosin flux (JIS K 5902) having a nominal composition of 10% solids by weight of water white rosin in methyl alcohol (JIS K 1501) solution.	No abnormalities shall be recognized in appearance. The electrical performance requirements specified in item 4 shall be satisfied.
	(3) Temperature and immersing time Temperature (°C) Time (s) Dip soldering 260± 5 10±1	
	Manual soldering 350±10 3+1	
		DEAUTIC NO

		<u></u>		(Push	
S	PUN-S-501	SPUN PRODUCT SPECIFICATIONS	, ,	,	
	Items	Test conditions		Criterion	
1	,	(4) Immersion depth : Immersion depth shall be at copper plating			
	1	portion for P.C.B. terminal after mounting.		,	
ļ		Thickness of P.C. board (Single sided copper			
		clad P.C.B.) : 1.6mm			
Į.]	•	
E 10	Destates to Class	0.44.1.1.11.1.1.1.1.1.1.1.1.1.1.1.1.1.1.	<u> </u>		
5.12	1		Flux shall not be risen up to contact.		
Į.	(Applied to the switch for P.C.	(1) Equipment : Auto-dip chamber (2) Solder : H63A (JIS Z 3282)	Shall be free from abnormalities in		
1	board)	(2) Solver . NOSA (315 Z 3202) (3) Flux : Rosin flux (JIS K 5902) having a nominal composition of 25%	operation.		
	Doar dy	solids by weight of water white rosin in methyl alcohol			
		(JIS K 1501) solution.	1	•	
		(4) Temperature : 260±5°C	ŀ		
		(5) Immersing time: 5±1 s	·		
ļ		(6) Immersion depth : Immersion depth shall be at copper plating		,	
1		portion for P.C.B. terminal after mounting.			
!		Thickness of P.C. board : 1.6 mm			
B 10	lunch i litu	- 11- 12- 12- 12- 12- 12- 12- 12- 12- 12			
· · · ·	urability Items	Test conditions	,	Culturian	
6.1	Operating life	Switch shall be operated 30,000 cycles at 15~20 cycles/minute without	Contact	Criterion	
***	without load	load.	Contact res 40 ∎Ω		
	#10.1046 10EG	10001		resistance (Item 4.2) :	
			10 MΩ		
				oof (Item 4.3):	
	•	•		OO V AC for 1 minute.	
		•		tric breakdown shall occur.	
				orce (Item 5.1):	
		•	Within	+10 -30 % of specified value.	
			No abnormal	ities shall be recognized	
				ce and construction.	
6.2	Operating life	Switch shall be operated 10,000 cycles at 15-20 cycles/minute with	Contact res	istance (Item 4.1) :	
	with load	30 V DC 0.1 A. (Resistive load)	<u>40</u> ∎Ω		
				resistance (Item 4.2):	
		·	<u>10</u> μΩ		
!!		•		of (Item 4.3):	
			Apply 500 V AC for 1 minute.		
			No dielectric breakdown shall occur.		
				orce (Item 5.1) :	
				30 % of specified value.	
				ities shall be recognized	
			_in_appearan	ce and construction.	
7. V	eather proof				
7.1	Items C. 1.1	Test conditions		Criterion	
7.1	Cold proof	After testing at -20±2°C for 96 hours, the switch shall be allowed to	_	istance (Item 4.1):	
ļ		stand under normal temperature and humidity conditions for 1 hour, and	<u>40</u> ±Ω		
Ī		then measurement shall be made within 1 hour.		resistance (Item 4.2) :	
	•	Water drops shall be removed.	_10_ ΝΩ		
,				of (Item 4.3) :	
1				O V AC for 1 minute. tric breakdown shall occur.	
		į daras ir salas ir s		tric preskdown shall occur.	
ŀ	. 1			30 % of specified value.	
J	•			ities shall be recognized	
				ce and construction.	
7.2	Dry heat	After testing at 85±2°C for 96 hours, the switch shall be allowed to		istance (Item 4.1):	
		stand under normal temperature and humidity conditions for 1 hour, and	<u>40</u> μΩ		
	`	then measurement shall be made within 1 hour.		resistance (Item 4.2):	
	!		<u>10</u> μΩ		
			Voltage prod	of (Item 4.3) :	
			Apply <u>50</u>	OO V AC for 1 minute.	
	`	·		ric breakdown shall occur.	
				orce (Item 5.1):	
		• •		30 % of specified value.	
				ities shall be recognized	
	ŀ		in appearanc	e and construction.	
		,		. ' 1	
		APPD, CHKD. DSGD.	TITLE	:	
		M. S. Jun, 4	9 3		
			, DRAWING		
and .		PAGE SYMB DATE APPD CHKD DSGD Kizze Johahachi V. Da	uo	(3/4)	

ALPS ELECTRIC CO., LTD.


SPUN-S-501 SPUN PRODUCT SPECIFICATIONS Items Test conditions Criterion After testing at 40±2°C and 90~95%RH for 96 hours, the switch shall Damp heat Contact resistance (Item 4.1) : be allowed to stand under normal temperature and humidity conditions _40_ mΩ HAX for 1 hour, and measurement shall be made within 1 hour after that. Insulation resistance (Item 4.2) : Water drops shall be removed. 10 HQ HIN Voltage proof (Item 4.3): Apply 500 V AC for 1 minute. Ho dielectric breakdown shall occur. Operating force (Item 5.1) : Within $\frac{\pm 10}{2}$ % of specified value. No abnormalities shall be recognized in appearance and construction. 7.4 Salt mist Switch shall be checked after following test. No remarkable corrosion shall be (1) Temperature : 35 ± 230 recognized in metal part. (2) Salt solution: 5±1% (Solids by weight) (3) Duration : 24±1 h · After the test, sait deposit shall be removed in running water. 7.5 Temperature After 5 cycles of following conditions, the switch shall be allowed to Contact resistance (Item 4.1) : stand under normal temperature and humidity conditions for 1 hour, and cycling _40_mΩ HAX measurement shall be made within 1 hour after that. Insulation resistance (Item 4.2) : Water drops shall be removed. <u>10</u> HQ HIH Voltage proof (Item 4.3) : 70±2°C -----Apply 500 V AC for 1 minute. No dielectric breakdown shall occur. Operating force (Item 5.1) : Within $\frac{+10}{-30}$ % of specified value. No abnormalities shall be recognized Norma l in appearance and construction. temperature -25±3℃ -----30 min min 10~ ~15 10~15 min **■i**n 1 cycle

Precaution in use

- Note that if the load is applied to the terminals during soldering they might suffer deformation and defects in electrical performance.
- 2. Use of water-soluble soldering flux shall be avoided because it may cause corrosion of the switch.
- 3. The knob should be mounted or demounted after single-lock releasing.

 If attempted under single locked condition, the single-acting mechanism may be damaged.
- Printed circuit board mounting hole diagram (±0.05 tolerance unless otherwise specified)





STRAIGHT TERMINALS

6 POLES 4 POLES 2 POLE

Lever

4 Soldering should be performed after single lock released. If attempted under single locked condition, the single-acting mechanism may be deformed by soldering heat.

APPD. CHKD. DSGD. TITLE

SINTER DESCRIPTION (A) JOHN PAGE SYHB DATE APPD CHKD DSGD (C, Z.o. Jakobash: J. Saito DRAWING NO.

CASE ALPS ELECTRIC CO., LTD.

