

Bench Top Power Supply



Specification Table

Output Voltage	Ch1, Ch2	0 to 32 V
	Ch3	-
Output Current	Ch1, Ch2	0 to 5 A
	Ch3	-
Overload Effect	CV $\leq 1 \times 10^{-4} + 2$ mV, CC ≤ 2 mA	
Ripple and Noise	CV ≤ 1 mVrms, CC ≤ 1 mA rms	
Regulation	CV - 20 mV (Typical Value), CC - 50 mV (Typical Value)	
Tracking Error	$5 \times 10^{-3} + 2$ mV	
Reliability	MTBF (e) : $\geq 2,000$ hours	
Other Features	Auto switching between voltage and current operation triple output, series or parallel operation, current limitation	

General Characteristics

Power	220 V $\pm 10\%$, 50 Hz $\pm 4\%$
LCD Size	Diagonal 178 mm (7 inches)
Product Net Weight	Around 4 kg
Product Size	210 mm \times 152 mm \times 305 mm
Standard Accessories	English manual and power cord
Standard Individual Packing	Gift Box
Standard Quantity Per Carton	2 pcs
Standard Carton Measurement	600 \times 380 \times 245 mm (0.056 CBM Per Export Carton)
Standard Carton Gross Weight	9.5 kg

Part Number Table

Description	Part Number
Power Supply, Bench, 2 \times 32 V, 5 A	72-8700

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. TENMA™ is the registered trademark of the Group. © Premier Farnell plc 2012.