

Bulkhead Adapter BNC Jack - TNC Jack



Specifications:

Electrical

Frequency Range : DC-4GHz
 Nominal Impedance : 50Ω
 Working Voltage Max : 500V
 Proof Voltage : 1,500V

Materials


Bodies : Brass per JIS-C3604
 Centre Contact : Brass per JIS-C3604
 Insulation : PTFE per ASTM D1457 and ASTM D1710

Mechanical

Interface in Accordance with : MIL-STD-348A

Environmental

Operating Temperature Range : -65°C to +165°C
 Hermetically Sealed



Mounting Hole

Dimensions : Millimetres (Inches)



Bulkhead Adapter BNC Jack - TNC Jack



Finish and Others

No	Description	Material	Qty	Finish
1	Nut	Brass	1	Nickel
2	Washer	Steel	1	Nickel
3	Gasket	Silicone	1	Red
4	Washer	Brass	1	Nickel
5	Insulation	PTFE	2	None
6	Body	Brass	1	Nickel 100µ" Min.
7	Hermetically Sealed	-	1	Nickel
8	Chassis	Brass	1	Nickel 100µ" Min.
9	Centre Contact	Brass	2	Gold 30µ" Min.

Part Number Table

Description	Part Number
Adapter, BNC Jack - TNC Jack, Bulkhead	R13-029-11-0026110KK

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.