

Connection diagram

Adjustable temperature

High switching capacity

Small hysteresis

Terminals easily accessible

Clip fixing

Change-over contact


The mechanical thermostat is used for controlling heating and cooling equipment, filter fans or signal devices. The thermostat registers the surrounding air and can switch both inductive and resistive loads via snap-action contact. Due to the integrated thermal feedback the switch temperature difference could be reduced. Functionality: The temperature setting on the scale equals to the upper switch point, which means that the NC contact opens. The temperature setting minus switch temperature difference (and tolerances) equals to the lower switch point, which means that the NC contact closes.



Technical Data

Switch temperature difference	5K (-3/+2K tolerance)*	
Sensor element	thermostatic bimetal	
Contact type	change-over snap-action contact	
Service life	> 100,000 cycles	
Min. switching capacity	10mA	
Max. switching capacity, NC	250VAC, 10 (4) A	
	120VAC, 10 (4) A	
	30WDC	
Max. switching capacity, NO	250VAC, 5 (2) A	
	120VAC, 5 (2) A	
	30WDC	
Max. inrush current	16AAC for 10 sec.	
Connection	4-pole terminal, clamping torque 0.5Nm max.:	
	rigid wire 2.5mm²	
	stranded wire (with wire end ferrule) 1.5mm ²	
Mounting	clip for 35mm DIN rail, EN 60715	
Casing	plastic according to UL94 V-0, light grey	
Dimensions	67 x 50 x 38mm	
Weight	approx. 0.1kg	
Fitting position	variable	
Operating / Storage temperature	-45 to +65°C (-49 to +149°F)	
Operating / Storage humidity	max. 90% RH (non-condensing)	
Protection type	IP20	
Approvals	UL File No. E164102	


*If the Normally Closed contact is used, the switch temperature difference could be reduced by connecting terminal "N" (RF heating resistor). It causes the thermal feedback which is subject to surrounding conditions and thus has to be determined for each individual application.




Enclosure heater

Signal device

Filter fan, Cooling equipment,



e.g. Filter fan



Examples of connection

Art. No.	Operating voltage	Setting range
01170.0-00	230VAC	+5 to +60°C
01170.0-01	230VAC	+40 to +140°F
01170.0-02	230VAC	-20 to +35°C
01170.9-00	120VAC	+40 to +140°F
01170.9-01	120VAC	+5 to +60°C